BILL'S HOME TECH

Home & Small Business Tech Solutions

AN EXTENDED GUIDE · NO. 2173

Updated November 2026

Why Cheap Printers Only Work on 2.4GHz Wi-Fi

The two "lanes" of home Wi-Fi — and how to put a budget printer on the right one

Plain-English printer help from:

Bill's Home Tech

Portage County, Ohio

Tech Made Simple. Service Made Personal.

Bill Davis — Bill's Home Tech

(330) 200-8042 · bill@billshometech.com · Atwater, Ohio

Book a visit · billshometech.com/book

What's Inside

Everything in this guide, with page numbers. Skip to whichever chapter answers your question right now.

The 60-Second Version 3

The Short Version 3

The Two Lanes of Wi-Fi, in Plain English 4

Why Budget Printers Skip the Fast Lane 4

How to Tell Which Lane You're Dealing With 5

Fix One: Point the Printer at the 2.4GHz Name 6

Fix Two: When Both Lanes Share One Name 6

The Temporary-Split Trick 7

The Phone-Must-Match Gotcha 8

Watch Out for the Guest Network 8

Why 2.4GHz Is Perfectly Fine for a Printer 9

Make It Stick 9

Where You Put the Printer Matters, Too 10

When to Call Bill 10

Everyday Cheat Sheet 12

A Note From Bill 13

Your Visit — and My Promise 14

SUMMARY

The 60-Second Version

Home Wi-Fi runs on two lanes — 2.4GHz (slow but far-reaching) and 5GHz (fast but short-range) — and many inexpensive printers can only use the 2.4GHz one. If your printer will not join the Wi-Fi, the fix is to connect it to the 2.4GHz network: pick the Wi-Fi name WITHOUT "5G" in it. If your two lanes share a single name, stand next to the router during setup, or split the names temporarily (a small router change).

When setting up with a phone app, put the phone on the 2.4GHz network first, because the app gives the printer whatever lane the phone is on. The slow lane is actually ideal for a printer, so this costs you nothing.

- Keep the printer on your MAIN network, not a "guest" one.
- A fixed address plus the 2.4GHz name makes it reliable for good.

1 The Short Version

You bought a perfectly good inexpensive printer, but it simply will not join your Wi-Fi — or it joins once and then vanishes. Before you blame the printer, there is a very common and completely fixable reason: many budget printers can only talk to one of the two "lanes" your Wi-Fi broadcasts on, called 2.4GHz. If your router is steering the printer toward the other lane, the printer never finds a network it can use.

This is not a defect and it is not something you did wrong. Once you understand the two lanes and point the printer at the right one, it connects and stays connected. This guide explains it in plain English and gives you the fixes in order.

- Home Wi-Fi usually runs on two "lanes": 2.4GHz and 5GHz.
- Many cheaper printers can only use the 2.4GHz lane.
- The fix is to make sure the printer connects to the 2.4GHz network, not the 5GHz one.
- 2.4GHz is actually the better lane for a printer anyway — so this costs you nothing.

TIP

If a brand-new printer will not join your Wi-Fi no matter how carefully you type the password, the 2.4GHz lane is the most likely culprit — not a broken printer. Work through this guide before returning anything.

2 The Two Lanes of Wi-Fi, in Plain English

Your router broadcasts Wi-Fi on two different radio bands, and it helps to picture them as two lanes on a road. The 2.4GHz lane is slower but travels far and passes through walls easily. The 5GHz lane is faster but does not reach as far and is more easily blocked by walls and furniture.

Fast devices like phones, tablets, and streaming boxes love the 5GHz lane for its speed. A printer, though, sends tiny amounts of information and does not need speed at all — it needs a steady, far-reaching signal, which is exactly what the slower 2.4GHz lane provides.

GOOD TO KNOW

Newer home Wi-Fi sometimes adds a third, even faster lane (6GHz). It makes no difference here — printers belong on the slow, reliable 2.4GHz lane regardless of how many fast lanes your router offers.

3 Why Budget Printers Skip the Fast Lane

Adding the hardware to use the 5GHz lane costs a little more to build. To keep prices low, manufacturers leave it out of many inexpensive printers, so those models can only ever see and join the 2.4GHz lane. Since a printer gains nothing from the fast lane, it is a sensible corner to cut — but it surprises people who do not know to look for it.

The trouble starts when your phone (sitting on the fast 5GHz lane) tries to set up a printer that can only see the slow lane, or when your router hides the 2.4GHz lane behind a single combined name. The printer looks for a network it recognizes, cannot find one, and quietly gives up.

WATCH OUT

A printer that will not connect to a brand-new router, right after your internet company swapped your equipment, is very often hitting exactly this lane mismatch — the new router combined both lanes under one name and steered the printer wrong.

4 How to Tell Which Lane You're Dealing With

You do not need special tools — you just need to look at your Wi-Fi network names. How they are set up tells you which situation you are in.

- If you see two Wi-Fi names that are nearly identical but one ends in something like "-5G" or "-5GHz," your lanes have separate names. The one WITHOUT the 5G label is the 2.4GHz lane — use that for the printer.
- If you see only one Wi-Fi name, your router combines both lanes under it (often called "band steering"). That is the setup most likely to confuse a budget printer.
- On your phone, the Wi-Fi settings screen often shows which network you are joined to — note the exact name so you can match the printer to it.

GOOD TO KNOW

The sticker on the side or bottom of many routers lists the network name(s) and password. If it shows two names, that confirms your lanes are separate — and tells you exactly which name to give the printer.

5 Fix One: Point the Printer at the 2.4GHz Name

If your two lanes have separate names, this is the whole fix: during the printer's Wi-Fi setup, choose the name WITHOUT the 5G label.

1. On the printer's screen, open Settings, then the Network or Wireless menu, and choose Wireless Setup Wizard.
2. When the list of networks appears, pick the one WITHOUT "5G" in the name.
3. Type the password for that network carefully — it is case-sensitive.
4. Wait for the connected confirmation, then print the printer's network test page if it offers one.

> **TIP**
>
> If your printer has no screen, use the maker's phone app to connect it — but first make sure your phone itself is joined to the 2.4GHz (non-5G) network, because the app hands the printer whatever network the phone is on.

6 Fix Two: When Both Lanes Share One Name

If you have only one Wi-Fi name, the router is combining both lanes and deciding which one each device gets — a feature often called band steering. Usually that is convenient, but it can keep a 2.4GHz-only printer from ever finding a lane it can use. There are a few gentle ways around it.

- On your phone, join that single Wi-Fi name and stand right next to the router while setting up the printer — being close often nudges devices onto the 2.4GHz lane.
- In the printer's app, follow the setup and give it the one network name and password; many routers will then connect the printer on 2.4GHz automatically.
- If it still will not join, the router may need a small setting change to let the printer find the 2.4GHz lane — covered next.

WATCH OUT

Splitting a combined Wi-Fi name into separate 2.4GHz and 5GHz names, or turning off band steering just long enough to connect the printer, is a small router change that I do often. It is quick when you know where the setting lives, and easy to get wrong by guessing — a good one to hand off.

Rather not do this yourself? I'll come to your home and set it up for you — a flat $99 first visit across Portage County, Ohio and nearby communities. Outside the area? I also help remotely by phone or screen-share. Book at billshometech.com/book or call (330) 200-8042.

7 The Temporary-Split Trick

One reliable workaround, if you are comfortable in your router's settings, is to temporarily give the two lanes different names, connect the printer to the 2.4GHz one, and the connection then holds even if you combine the names again later.

1. Sign in to your router's settings (usually in a web browser or the router's app).
2. Find the Wi-Fi or Wireless settings and look for the 2.4GHz and 5GHz sections.
3. Give the 2.4GHz network a slightly different name temporarily, and save.
4. Connect the printer to that 2.4GHz name using the steps above.
5. Once the printer is connected, you can leave the names split or recombine them — the printer usually stays connected either way.

WATCH OUT

Router settings vary a great deal between brands and providers, and a wrong change can knock your whole house offline for a few minutes. If you are not fully confident, this is a sensible point to call for help rather than experiment.

8 The Phone-Must-Match Gotcha

Here is a subtle trap worth calling out. When you set up a printer using a phone app, the app usually assumes the printer should join whatever network the phone is currently on. If your phone is on the fast 5GHz lane, the app may try to push the printer onto a lane it cannot use — and setup fails for a reason that has nothing to do with the printer.

1. Before starting the app setup, open your phone's Wi-Fi settings.
2. Join the 2.4GHz (non-5G) network so the phone and printer will match.
3. Run the printer app's setup; the printer joins the same lane the phone is on.
4. Once the printer is connected, you can switch your phone back to the faster lane — the printer stays put.

> **GOOD TO KNOW**
>
> This is also why a setup can fail one day and work the next with no changes — the phone happened to be on a different lane each time. Matching them on purpose removes the guesswork.

9 Watch Out for the Guest Network

Many routers offer a separate "guest" Wi-Fi network for visitors. It is easy to accidentally put the printer on the guest network, or to have your phone on the main network and the printer on the guest one — and devices on a guest network often cannot see the rest of the house on purpose.

- Make sure the printer is on your MAIN home network, not a guest network.
- Make sure your computer and phone are on that same main network.
- If you are not sure which is which, the guest name often includes the word "guest."

> **TIP**
>
> If everything looks right but the printer still cannot be reached, a mismatched main-versus-guest network is a frequent hidden cause — worth a quick check before anything more technical.

10 Why 2.4GHz Is Perfectly Fine for a Printer

It is natural to feel short-changed that your printer uses the "slow" lane, but for printing it genuinely does not matter. A printer sends only small bursts of information, and the 2.4GHz lane's longer reach actually makes the connection more dependable — especially if the printer sits in a back room or down the hall from the router.

So the 2.4GHz-only limitation, once you have worked around it, costs you nothing in everyday use. Your documents and photos print exactly as fast as they ever would.

> *For a printer, the slow, far-reaching lane is the right lane — steadiness beats speed.*

11 Make It Stick

Once the printer is happily on the 2.4GHz lane, a couple of small steps keep it that way so you are not doing this again after the next power blip.

- If your lanes have separate names, leave them that way — it makes future setups foolproof.
- Giving the printer a fixed address in the router (a reservation) stops it wandering — a worthwhile companion fix.
- Write your 2.4GHz network name and password on a card by the printer for next time.

GOOD TO KNOW

A fixed address plus a known 2.4GHz name is the combination that makes a budget printer behave like an expensive one — reliable and forgettable in the best way.

12 Where You Put the Printer Matters, Too

Because budget printers live on the far-reaching 2.4GHz lane, they usually hold a signal well even in a back room — but placement can still make the difference between rock-solid and flaky. A few simple habits keep the connection strong once you have it.

- Keep the printer within reasonable reach of the router — the 2.4GHz lane travels far, but very thick walls, metal filing cabinets, and large appliances still weaken it.
- Avoid tucking the printer inside a metal cabinet or right beside a microwave or cordless-phone base, which can interfere with the 2.4GHz signal.
- If the printer sits far from the router and keeps dropping, a USB cable or moving the printer closer are both simple cures.
- A mesh Wi-Fi system or an extender can carry the 2.4GHz signal to a distant room if moving the printer is not an option.

GOOD TO KNOW

The 2.4GHz lane is the same band many older cordless phones, baby monitors, and microwaves use, so a printer that works everywhere except right next to one of those is probably hitting a little interference — a few feet of distance usually clears it.

13 When to Call Bill

Getting a budget printer onto the right Wi-Fi lane is usually a five-minute job once you know which lane to use — and this guide gets most people there. But if your Wi-Fi uses a single combined name, if the router needs a setting change, or if you have simply had enough of wrestling with it, you do not need to keep trying.

I come to you, point the printer at the right lane, split or adjust the router settings if needed, and confirm it holds steady before I leave. If your internet was just changed and other devices got orphaned too, I will reconnect them in the same visit.

- Your Wi-Fi has one combined name and the printer will not join.
- The router needs a setting change you would rather not make yourself.
- A brand-new printer refuses a brand-new router despite careful setup.
- You would simply like it connected and reliable for good.

CHEAT SHEET

Everyday Cheat Sheet

Keep this by the printer. Printers belong on the slow, steady lane.

I want to...	Do this...
Find the right network	Pick the Wi-Fi name WITHOUT "5G" in it — that is the 2.4GHz lane
Connect (has a screen)	Printer Settings Network Wireless Setup pick the non-5G name
Connect (no screen)	Put your PHONE on the non-5G network first, then run the maker's app
Only one Wi-Fi name?	Stand next to the router during setup; or split the lanes (ask Bill)
Avoid a hidden trap	Keep the printer on your MAIN network, never a "guest" one
Make it stick	Give the printer a fixed address so it stops wandering
Get help	Call Bill: (330) 200-8042

BEFORE YOU GO

A Note From Bill

A quick note from Bill. I write these guides to make home tech a little less frustrating, and I do my best to keep every step accurate and up to date. Still, every home, device, and setup is a bit different, so I can't promise a guide will match yours exactly or fix your particular problem. These guides are for general information only — they're not professional, legal, or financial advice, and they don't replace your device's own manual or the manufacturer's instructions. Please go slow, use your own good judgment, and use everything here at your own risk. If a step involves electrical wiring, a gas appliance, a water heater, plumbing, or climbing a ladder — or if anything just doesn't feel safe — please stop and call a licensed professional (or give me a call at 330-200-8042). Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results.

HOW I CAN HELP

Your Visit — and My Promise

You don't have to remember all of it — just that a friendly, patient person is one call away, whenever you'd rather have a hand.

KEY SPECS

In your home — $99 flat for the first visit, no contracts and no surprises, with a 30-day come-back-free follow-up. In-home visits cover Portage County, Ohio and nearby communities.
Outside the area? Remotely — $49 for a screen-share session (free for Support Plan members, $39/mo), refundable if I can't fix it — and credited toward a visit if you'd rather have me in person. Book either at billshometech.com/book.

GOOD TO KNOW

My promise — If you're not 100% satisfied with your visit, I'll come back at no charge, or refund the full $99. No questions, no awkwardness. That's how I'd want to be treated.

Whenever you're ready, I'll come to your home anywhere in Portage County, Ohio and nearby communities, at your pace. Too far for a house call? I also help remotely. Book at billshometech.com/book or call (330) 200-8042. — Bill

Call or text (330) 200-8042 · bill@billshometech.com

This free guide is for general information only — not professional advice, and no substitute for your device's own manual. Any prices or outside products mentioned can change; please confirm current details before you buy. Please use your own good judgment and follow it at your own risk — for anything involving electricity, gas, water, or heights, stop and call a licensed professional. Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results. © 2026 Bill's Home Tech, LLC.