



Keeping a 12-Volt Car Battery Healthy — Tenders, Winter & Jump Packs

Keeping a 12-volt battery healthy Tenders, winter and jump packs An Extended Guide · No. 1930

————— An Extended Guide · No. 1930 —————

Tech Made Simple. Service Made Personal.

Bill Davis — Bill's Home Tech

(330) 200-8042 · bill@billshometech.com · Atwater, Ohio

Book a visit — billshometech.com/book

What's Inside

Everything in this guide, with page numbers. Skip to whichever chapter answers your question right now.

1. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	5
2. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	6
3. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	7
4. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	8
5. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	9
6. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	10
7. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	11
8. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	12
9. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	13
10. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	14
11. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	15

12. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	16
13. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	17
14. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	18
15. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	19
16. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	20
17. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	21
18. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	22
19. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	23
20. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	24
21. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	25
22. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	26
23. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	27
24. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech	27

A Picture to Follow Along 28

A Second Look 29

A Note From Bill 29

Your Visit — and My Promise 30

1. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

What's Inside Everything in this guide, with page numbers. Skip to whichever chapter answers your question right now..... 4

1. The 60-Second Version.....	4
2. What the 12-Volt Battery Does.....	5
3. How Long a Battery Lasts.....	6
4. Signs of a Weak Battery.....	6
5. Why Slow Cranking Happens.....	7
6. That Clicking Sound.....	8
7. Why Cold Is So Hard on Batteries.....	8
8. Why Short Trips Hurt.....	9
9. Heat Wears Batteries Out.....	10
10. Cleaning Corrosion Safely.....	11
11. Checking the Terminals and Cables.....	11
12. Keeping Terminals Clean Longer.....	12
13. What a Maintainer Is.....	12
14. When a Maintainer Earns Its Keep.....	13
15. Hooking Up a Maintainer.....	14
16. Parasitic Drain Explained.....	14
17. Tracking Down a Drain.....	15
18. Free Battery Testing.....	15
19. Replace It or Just Charge It?.....	16
20. Choosing a Replacement Battery.....	17
21. Lithium Jump Packs	

2. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

..... 17	22. Keeping a Jump Pack Ready..... 18	23. Heat, Cold, and Where to Keep It..... 18	24. Sizing the Pack to Your Engine..... 19	25. Connecting a Jump Pack Safely..... 19
26. The Order for Taking It Off..... 20	27. No Sparks Near a Battery..... 20	28. The Handy Extras on a Jump Pack..... 21	29. Jumper Cables or a Jump Pack?..... 22	30. A Simple Winter Car Kit..... 22
31. Storing a Vehicle for the Season..... 23	32. The Short Version..... 23	33. When to Call Bill..... 24	Everyday Cheat Sheet..... 25	A Picture to Follow Along..... 26
A Second Look..... 26	A Note From Bill..... 27	Your Visit — and My Promise		

START HERE

3. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

1. The 60-Second Version If you only read one page, read this one. The battery under your hood does two jobs: it starts the engine and it steadies the car's electronics. Most last three to five years, then quietly fade. The good news is you can see trouble coming and head it off. A battery that cranks the engine slowly, makes the dash lights flicker, or just clicks when you turn the key is telling you it is tired. Longer drives, clean terminals, and a maintainer for a car that sits will add years. And a charged jump pack in the trunk means a dead battery is a five-minute hiccup, not a ruined afternoon. I want to take the fear out of this for you, because batteries have a reputation for being greasy, dangerous mysteries under the hood. They are not. With a few plain ideas and a couple of safety rules you will have down in five minutes, you can keep a battery healthy for years and rescue yourself from a dead one without flagging down a stranger. Most of what I am about to tell you is simply knowing what the signs mean and doing small, easy things at the right time. You can absolutely handle this. Batteries last about three to five years; plan for it. Slow cranking, dim lights, or clicking means a weak battery. Short trips and cold weather are hard on batteries. A charged lithium jump pack is cheap insurance against being stranded. WATCH OUT A car battery can give off hydrogen gas, which is flammable. Keep sparks, cigarettes, and flames well away whenever you work near one. THE BASICS 2. What the 12-Volt Battery Does Small box, two big jobs. That heavy box under the hood is a 12-volt battery, and nearly every ordinary gas car has one, including hybrids. Its first job is to deliver a big jolt of power to the starter motor so the engine turns over. Its second, quieter job is to keep the car's electronics steady — the clock, the radio presets, the computer settings — even when the engine is off. Once the engine is running, a part called the alternator takes over and recharges the battery as you drive. So the battery mostly works hard for a few seconds at startup, then rides along getting topped back up.

GOOD TO KNOW

4. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

Because the battery mostly rests while you drive and only works hard for those few seconds at startup, people are often surprised when it fails — the car seemed fine. But those startup jolts, day after day, year after year, gradually wear the battery down inside where you cannot see it. Add in the heat of summer and the cold of winter, and a battery that felt perfectly strong can reach the end faster than you would guess. That is why knowing the warning signs matters more than how the car felt yesterday. Even an electric car has a small 12-volt battery for its electronics, separate from the big drive battery. When an EV 'won't wake up,' it is often that little 12-volt battery, not the expensive one.

LIFESPAN 3. How Long a Battery Lasts Three to five years is the honest range. A typical car battery lasts somewhere between three and five years. Some stretch longer with gentle use and a mild climate; some die at two in brutal heat or cold. There is no warning bell at the end — a battery that started the car fine all week can fail to turn it over on a frosty morning. That is why age matters as much as symptoms. If you know your battery is pushing five years, treat any hint of weakness seriously and think about replacing it on your schedule rather than waiting for it to strand you. Because there is no warning bell at the end of a battery's life, I tell people to let the calendar be their guide as much as the symptoms. If you know your battery went in four or five years ago, treat the first cold morning hesitation as a serious hint rather than a fluke. Replacing a battery on a warm afternoon in your own driveway, on your schedule, is a small chore. Replacing one in a freezing parking lot when it has left you stranded is a miserable afternoon. Age is the clue that lets you choose the easy version. **TIP** Find the date on the battery. Many have a sticker or a stamped code showing the month and year they were made. Knowing the age takes the guesswork out of when to replace.

WARNING SIGNS**5. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

4. Signs of a Weak Battery Your car will usually warn you first. A dying battery rarely goes without a goodbye. The clearest sign is slow cranking — when you turn the key, the engine turns over sluggishly, like it is wading through molasses, instead of springing to life. You may also notice the dashboard and headlights going dim or flickering, especially at startup or when idling. The radio may reset, or the power windows may crawl. Any of these means the battery is struggling to hold and deliver its charge. Catch it at this stage and you replace on your terms, not stuck in a parking lot. The kind thing about a dying battery is that it usually gives you several of these warnings before it quits entirely, often over a week or two. One slow crank on a cold morning might be nothing; slow cranks several mornings running, plus a dimming dash, are the battery clearly telling you its time is short. The moment you notice a cluster of these signs, that is your cue to get it tested and plan a replacement, rather than hoping for a few more weeks and getting caught out when the temperature drops. Slow, labored cranking when you turn the key. Dim or flickering dashboard and headlights. Radio presets or clock resetting on their own. The battery warning light on the dash coming on. A rotten-egg smell under the hood, which means a battery problem. SLOW CRANK

5. Why Slow Cranking Happens The starter is begging for more power. Let me explain slow cranking, because it is the single most useful symptom to recognize. Starting the engine demands a huge burst of electricity for a second or two. A healthy battery delivers it instantly and the engine spins right up. A weak battery cannot push out that burst fast enough, so the starter motor turns the engine over slowly and reluctantly. That lazy, drawn-out crank is the battery saying it is nearly out of strength. It might still start the car a few more times, but it is living on borrowed time. Slow cranking is the symptom I most want you to recognize, because it is the clearest early warning of all. A healthy battery turns the engine over fast and crisp; a tired one turns it over slow and labored, like the engine is wading through mud. It may still fire up for a while

GOOD TO KNOW

6. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

yet, but that lazy crank is the battery telling you plainly that its strength is fading. Catch it at this stage and you replace the battery on a mild afternoon in your own driveway, rather than in a freezing lot after it finally quits. Slow cranking in the cold is not always a bad battery. Cold thickens the engine oil too, making it harder to turn. But a battery that cranks slowly on a warm day is almost certainly weak. THE CLICK 6. That Clicking Sound One click or a rapid chatter, both point to power. The clicking so many people describe is a classic. When you turn the key and hear a single sharp click, or a rapid machine-gun chatter, and the engine does not turn over, the battery is too weak to run the starter. The click is a little switch called the solenoid trying to do its job without enough power behind it. It almost always means a dead or very weak battery, or sometimes a bad connection at the terminals. A jump pack or a jump from another car will usually get you going so you can sort it out. The clicking is worth knowing because people so often mistake it for a bigger, costlier problem. A single sharp click, or a rapid chatter, with the engine refusing to turn, almost always means the battery is simply too weak to run the starter, not that the engine or starter is broken. A jump pack or a jump from another car will usually get you going straight away. Once you recognize that click for what it is, it loses its power to frighten you; it is just the battery asking for a boost, not the end of the car. WATCH OUT Rapid clicking with the dash lights dimming hard is a near-dead battery. A single click with everything else also dead could be a loose or corroded terminal. Check the connections before assuming the worst.

COLD WEATHER**7. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

7. Why Cold Is So Hard on Batteries Winter can halve a battery's punch. Ohio winters are tough on batteries, and here is why. The chemistry inside a battery slows way down when it is cold. On a frigid morning a battery may have only about half the cranking power it has on a mild day. At the very time the engine is hardest to start — thick cold oil, stiff everything — the battery is at its weakest. That is why batteries so often die on the first really cold snap of the year. A battery that was merely tired in the fall gives up entirely in January. I bring this up every autumn with my Ohio customers because the timing is so predictable. A battery that has been quietly weakening all summer still manages to start the car through the mild fall. Then the first hard freeze arrives, cuts its power roughly in half, and the engine won't turn over on the coldest morning of the year — usually when you most need to be somewhere. If your battery is getting on in years, testing or replacing it before winter settles in is one of the smartest, cheapest bits of prevention there is. Cold roughly halves a battery's available cranking power. Cold engine oil is thicker, so the engine is harder to turn. The first hard freeze is when weak batteries commonly fail. A battery pushing four or five years is worth replacing before winter.

SHORT TRIPS

8. Why Short Trips Hurt The alternator never gets to catch up. This one surprises people. Every time you start the car, the battery spends a big chunk of its charge. The alternator refills it as you drive — but only if you drive long enough. If all your trips are five minutes to the store and back, the alternator never fully replaces what starting used up. Over weeks the battery sinks lower and lower, running chronically half-empty, which wears it out early and leaves it vulnerable to a cold morning. Lots of short hops are, oddly, harder on a battery than one long highway trip. If your life is mostly short hops, you do not have to change how you live — you just have to give the battery a real charge now and then. Take the long way home once a week, or run a half-hour drive on the weekend, so the alternator can fully top the battery back up. Or, if the car lives at home with an outlet nearby, a maintainer does the same job in the driveway

TIP**8. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

while you sleep. Either way, the goal is simply to let the battery reach a full charge on a regular basis instead of always running half-empty. If your driving is mostly short errands, take the car for a longer drive now and then, or put it on a maintainer at home, to let the battery get fully charged. HEAT TOO 9. Heat Wears Batteries Out Summer is the quiet killer. We blame winter, but heat may do more lasting harm. High temperatures speed up the chemistry inside the battery and evaporate the fluid, which ages it faster even though it keeps starting the car fine. The damage is invisible until a cold day exposes the weakened battery. That is the cruel trick: a hot summer quietly cooks the battery, and the following winter finishes it off. It is why batteries often seem to 'die in the cold' when the real wear happened months earlier in the heat. I always remind my Ohio customers that summer does quiet damage even though we blame winter. The heat speeds up the chemistry inside the battery and evaporates its fluid, aging it faster than you would ever guess while it keeps starting the car just fine. Then the first cold morning exposes the weakened battery and everyone says it died in the cold. The truth is the cold only finished off what the summer heat started months earlier. Parking in the shade or a garage through the hot months is a small kindness that genuinely stretches a battery's life. GOOD TO KNOW Parking in shade or a garage in summer is a small kindness to your battery. Less heat means a slower-aging battery.

CORROSION**9. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

10. Cleaning Corrosion Safely That white fuzz is choking the connection. Open the hood and you may see a crusty white, blue, or green powder built up on the battery terminals. That corrosion gets between the battery and the cables and blocks the flow of power, so the car may crank slowly or not start even with a good battery underneath. The fix is a simple home job with baking soda and water, done in the right order and with care, because you are working around a battery that can spark and gives off flammable gas. Take your time with this little job and it is perfectly safe and genuinely satisfying — a crusty, struggling battery can come back to life with ten minutes of cleaning. The baking-soda-and-water mix neutralizes the acid in the corrosion, which is why it fizzes as you scrub. Just keep that paste off the car's paint, wear your gloves, and keep your face back. When you are done and everything is reconnected in the right order, you will often find the car cranks noticeably stronger, all from clearing away a bit of fuzz that was choking the connection.

- 1** Turn the car off and let it sit. No sparks, flames, or smoking nearby.
- 2** Put on gloves and eye protection; battery crust is caustic.
- 3** Disconnect the negative cable first (the one marked with a minus sign), then the positive.
- 4** Mix a spoonful of baking soda in a cup of water and scrub the terminals with an old toothbrush.
- 5** Rinse lightly, dry everything, then reconnect positive first and negative last. **WATCH OUT** Always disconnect the negative cable first and reconnect it last. Doing it the other way risks a big spark against the car body.

CONNECTIONS**10. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

11. Checking the Terminals and Cables Loose or dirty connections fake a dead battery. While you are in there, give the connections a once-over. The cable clamps should be snug on the posts — if you can wiggle a clamp by hand, it is loose and needs tightening. Look for frayed or cracked cables too. A surprising number of 'dead battery' no-starts are really just a loose or corroded connection starving a perfectly good battery. Tightening a clamp or cleaning a post with a wire brush can bring a car right back to life. It costs nothing and takes five minutes, so it is always worth a look before you condemn the battery. Before you ever condemn a battery as dead, give the connections a good look, because a loose or crusty clamp can fake a dead battery perfectly. Try to wiggle each cable clamp with your hand; a healthy one will not budge. Look for frayed cables and that telltale white or green fuzz. A surprising share of no-start calls I get turn out to be nothing more than a loose clamp or a corroded post starving a perfectly good battery. Tightening a clamp or cleaning a post costs nothing and takes five minutes, and it is always worth checking first. Try to wiggle each cable clamp; it should not budge. Look for green or white crust, and for frayed cables. Tighten loose clamps with the right-size wrench. A loose connection can mimic a dead battery exactly. PROTECT 12. Keeping Terminals Clean Longer A little grease buys a lot of time. Once the terminals are clean and tight, you can slow corrosion from coming back. A thin smear of dielectric grease or petroleum jelly on the posts, or a pair of felt anti-corrosion washers that slip over them, keeps moisture and acid fumes off the metal. It is a two-minute step that can keep the connections clean for a year or more. You do not need anything fancy — the goal is just to seal the bare metal from the air so that white fuzz has a harder time forming. TIP Auto-parts stores sell little felt washers and a spray made just for battery terminals. They are cheap and they genuinely cut down on corrosion.

MAINTAINERS**11. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

13. What a Maintainer Is A gentle charger for a car that sits. A battery maintainer, sometimes called a trickle charger or a tender, is a small device that plugs into the wall and connects to the battery to keep it topped up. It is not a fast charger for reviving a dead battery in a hurry. Instead it delivers a slow, gentle charge and then backs off automatically when the battery is full, so it can stay connected for weeks or months without overcharging. For any vehicle that sits unused, a maintainer is the single best thing you can do to keep its battery healthy. The word 'charger' confuses people, so let me be clear about the difference. A maintainer is not for reviving a dead battery in a hurry — that is a job for a bigger charger or a jump. A maintainer is for keeping an already-good battery topped up over long stretches of sitting. It sips a gentle current in, senses when the battery is full, and then idles, so it will never overcharge or harm the battery no matter how many weeks it stays plugged in. Set it and forget it is exactly how a maintainer is meant to work. **GOOD TO KNOW** A good maintainer is 'smart' — it senses the battery and switches itself between charging and idling. You can leave it hooked up all winter and come back to a fully charged battery. **WHEN TO USE** 14. When a Maintainer Earns Its Keep Anything that sits for weeks wants one. The maintainer shines for vehicles that do not get driven regularly. A classic car tucked away for winter, a motorcycle parked for the season, an RV or camper between trips, a boat, a second car that only comes out on weekends, or a snowbird's vehicle left behind for months — all of these will slowly drain and ruin a battery if left alone. Hook up a maintainer and the battery stays full and ready. It is far cheaper than replacing a battery, or a whole set of them, every spring. Classic or collector cars stored for winter. Motorcycles, boats, and RVs between seasons. A second or weekend-only car that sits most days. Any vehicle left behind while you travel for weeks.

HOOKUP**12. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

15. Hooking Up a Maintainer Two clamps and a wall plug. Connecting a maintainer is simple and safe if you follow the order. Most come with a set of clamps or a small ring connector you can leave bolted to the battery permanently with a little plug that dangles out for easy hookup. The leave-it-attached style is lovely for a motorcycle or classic — you just plug in the cord and walk away. Whichever you have, connect to the battery before plugging the charger into the wall, and unplug from the wall before removing the clamps. The one thing to get right with a maintainer is the order, and it is easy. Connect the clamps to the battery before you plug the maintainer into the wall, and unplug it from the wall before you remove the clamps. That simple sequence keeps any spark away from the battery, where it could meet the gas a battery gives off. Many maintainers come with a little ring connector you can leave bolted to the battery permanently, with a plug that dangles out, which is lovely for a motorcycle or classic since you just plug in the cord and walk away.

- 1** Make sure the maintainer is unplugged from the wall to start.
- 2** Clip the red clamp to the positive post (marked with a plus).
- 3** Clip the black clamp to the negative post or a bare metal spot.
- 4** Now plug the maintainer into the wall outlet.
- 5** To remove: unplug from the wall first, then take off the clamps. **WATCH OUT** Plug into the battery first and the wall last. Plugging into a live outlet before the clamps are set can throw a spark right at the battery.

DRAIN**13. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

16. Parasitic Drain Explained Something stays awake after you walk away. Modern cars never fully go to sleep — alarms, clocks, keyless entry, and computers all sip a trickle of power while parked. That normal trickle is called parasitic drain, and a healthy battery shrugs it off for weeks. The trouble starts when something draws more than it should: a glovebox light that stays on, an aftermarket gadget wired in wrong, or a module that refuses to power down. A heavy parasitic drain can flatten a good battery overnight or over a few days, leaving you baffled because the battery itself is fine. The reason parasitic drain fools people is that the battery itself is perfectly healthy — a store test will say it is fine, and once charged it starts the car without complaint. Then the car sits a day or two and goes dead again, and round and round you go, baffled. The trick is to recognize the pattern: a good battery that keeps going flat when the car sits is almost never a bad battery. It is something staying awake and drawing power it shouldn't, and that is a different problem to chase down. **GOOD TO KNOW** If a fairly new battery keeps going dead when the car sits a day or two, suspect a parasitic drain rather than a bad battery. It is a common, fixable problem. **FIND DRAIN** 17. Tracking Down a Drain Sometimes it is something obvious. Before anyone reaches for meters, it is worth checking the easy culprits. A trunk, glovebox, or vanity-mirror light that stays lit when it should go off is a frequent offender. A phone charger or dash cam left plugged into a 'always-on' socket can do it too. Open and close each door, check that interior lights actually go off, and unplug anything you added to the car. If the mystery drain continues after that, it is time for a shop or someone like me to measure where the power is leaking out, because the next step needs a meter. Check that trunk, glovebox, and dome lights go off. Unplug dash cams, chargers, and any added gadgets. Make sure every door is latching fully. If it still drains, have someone measure the current draw.

FREE TEST

14. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

18. Free Battery Testing The auto-parts store will check it for nothing. Here is a tip that saves money: most auto-parts stores will test your battery for free, right in the parking lot. They clip on a tester, you wait a minute, and it tells you whether the battery is good, weak, or ready to be replaced. It also checks the alternator's charging. There is no charge and no obligation to buy. If your car has been cranking slowly or the battery is getting old, a free test takes the guesswork out — you will know whether you have a year left or should replace it now. The free test at the parts store is the honest tiebreaker whenever you are unsure, and I lean on it constantly. They clip a tester on, you wait a minute, and it tells you plainly whether the battery is good, weak, or finished, and it checks the alternator's charging too. There is no charge and no obligation to buy anything. Just make sure the battery is charged up before the test; if it is flat from sitting, drive the car or charge it first, or the test may unfairly condemn a battery that was only discharged, not worn out. TIP Have the test done with the battery fully charged for an honest reading. If the battery is flat, charge or drive the car first, or the test may unfairly condemn a battery that is just discharged. REPLACE OR CHARGE 19. Replace It or Just Charge It? Know which problem you actually have. When a car won't start, people jump to 'I need a new battery,' but that is not always so. If the battery simply ran down — you left the lights on, or the car sat too long — then charging it, or a jump plus a good long drive, brings it right back. If the battery is worn out from age, charging only buys a little time before it fails again. The free store test is what tells the two apart. Pay to replace a battery that is genuinely done; just charge one that only got drained. Getting this diagnosis right saves real money. A battery that merely ran down because you left the dome light on, or because the car sat for three weeks, does not need replacing — a jump and a good long drive, or a few hours on a charger, brings it right back as good as before. Only a battery that is genuinely worn out from age needs your money. The free test

CHOOSING

15. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

at the parts store is what tells the two apart honestly, so you are not buying a new battery when all the old one needed was a charge. Situation What it needs Left a light on overnight Jump and a long drive, or a charge Battery is four or five years old and weak Replace it Goes dead when the car sits a day Hunt down a parasitic drain Slow crank only on cold mornings Test it; may be near the end 20. Choosing a Replacement Battery Match it to your car and climate. When it is time for a new battery, the main things are the group size — the physical size and terminal layout that fits your car — and the cold-cranking rating, which is how much starting power it provides in the cold. Your owner's manual or the parts-store lookup will tell you the right group size; do not guess, because the wrong size won't fit or clamp properly. For our Ohio winters, choosing a battery at or above the cranking rating your car calls for is money well spent. A stronger battery starts easier on the coldest mornings. A tidy folder of battery receipts is worth more than it looks. Most batteries carry a warranty — often a few years of free replacement and then a prorated period after that — but the warranty is only as good as your proof of when you bought it. If a battery dies early, that dated receipt can get you a free or discounted replacement. Keep the receipt, and jot the install date right on the battery with a marker, and you will never be left arguing with a parts counter about how old it is. GOOD TO KNOW Keep the receipt and note the install date. Most batteries carry a free-replacement and prorated warranty, and the date proves how old it is if it fails early.

JUMP PACKS**16. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

21. Lithium Jump Packs A pocket-sized rescue for a dead battery. Now to my favorite bit of gear: the lithium jump pack. These are small, light boxes — some not much bigger than a paperback — that hold enough punch to start a dead car all by themselves, no second car needed. You clip the two cables to your battery, press a button, and start the engine. They have mostly replaced the old bulky jump boxes and the need to flag down a stranger. A charged jump pack in your glovebox or trunk turns a dead battery from a crisis into a minor inconvenience. What I love about these little lithium packs is how they turn a dead battery from a ruined afternoon into a five-minute hiccup. There is no waiting for a tow, no flagging down a stranger, no second car needed; you clip on the pack, press the button, and start your own car. They have mostly replaced the old bulky jump boxes, and the good ones are small enough to live in a glovebox. A charged pack in the car means a dead battery simply stops being something to dread, and that peace of mind is worth every dollar. Small and light enough to live in the glovebox or trunk. Start a dead car with no second vehicle needed. Most also charge phones and have a built-in flashlight. A brand like NOCO is one well-known example type, not the only one. **KEEP CHARGED**

22. Keeping a Jump Pack Ready A dead jump pack helps nobody. The one rule that makes or breaks a jump pack is keeping it charged. It is no help if it is flat the day you need it. Lithium packs slowly lose charge just sitting, so top it up every few months whether you have used it or not. Many have a little battery gauge you can glance at. Pick a routine — recharge it when you change the clocks, say — and your pack will be ready whenever a dead battery surprises you. An uncharged jump pack is just a paperweight in the trunk. **TIP** Set a reminder on your phone every few months to top up the jump pack. It takes an hour on the charger and it is the whole point of owning one.

STORAGE**17. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

23. Heat, Cold, and Where to Keep It Don't bake it or freeze it. Lithium packs do not love extreme temperatures. A pack left baking on a hot dashboard all summer will age fast and could even be unsafe; one left to freeze solid in a glovebox all winter may refuse to deliver its power when you need it. The sweet spot is to keep it out of direct sun and, ideally, bring it inside during the harshest heat or cold. If it must live in the car, tuck it in the trunk or a glovebox out of the sun rather than on the dash. Lithium packs do not like extremes, so where you keep yours matters more than people expect. A pack left baking on a sunny dashboard all summer ages fast and can even become unsafe, while one frozen solid in a glovebox all winter may refuse to deliver its power the morning you need it. The sweet spot is cool and out of direct sun, and ideally brought indoors during the harshest heat or cold. If it must ride in the car, tuck it in the trunk or a shaded glovebox rather than up on the dash. **WATCH OUT** Never leave a lithium jump pack sitting on a sunny dashboard. Heat is hard on lithium batteries and, in the worst case, can make them swell or fail. **SIZING** 24. Sizing the Pack to Your Engine A big truck needs a bigger pack. Jump packs come in different strengths, and you want one matched to your engine. A pack rated for a small four-cylinder car may struggle or fail to turn over a big V8 truck or a diesel. The pack's box lists what size engine it handles — look for the peak amps and the engine range. When in doubt, buy a size up; a pack with power to spare starts your car easily and has reserve for a very cold day. One that is marginal for your engine may give up halfway through the job. Matching the pack to your engine is the step people skip, and then they are disappointed when a small pack cannot turn over a big truck. The pack's box lists the engine size it handles; look at the peak amps and the range of engines it covers. When you are between sizes, buy up rather than down, because a pack with power to spare starts the car easily and keeps a reserve for a bitter-cold morning when everything is harder. A pack that is

CONNECTING

18. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

merely adequate on a mild day may give up halfway through the job in January.

Check the pack's rating against your engine size. Small cars need less; big trucks and diesels need much more. When unsure, choose a larger-capacity pack for headroom. Cold weather means you want extra margin, not just enough. 25. Connecting a Jump Pack Safely Red to plus, black to bare metal. Using a jump pack is easy, but the hookup order keeps it safe. With the pack switched off, clip the red clamp to the positive battery terminal, marked with a plus sign. Then clip the black clamp not to the battery's negative post but to a clean, bare metal part of the engine or frame, away from the battery. That last bit matters: grounding away from the battery keeps any small spark away from the gas the battery can give off. Then turn the pack on and start the car.

- 1 Make sure the jump pack is switched off.
- 2 Clip the red clamp to the positive (+) battery terminal.
- 3 Clip the black clamp to bare metal on the engine or frame, away from the battery.
- 4 Turn the pack on and start the engine.
- 5 Once running, turn the pack off and remove black first, then red. **WATCH OUT** Grounding the black clamp away from the battery is not fussiness. It keeps sparks away from the hydrogen gas a battery can release, which is how battery explosions happen. **DISCONNECT** 26. The Order for Taking It Off Reverse of how you put it on. When the car is running, you remove the clamps in the reverse order you put them on. Switch the jump pack off first. Then take off the black clamp, then the red clamp, and keep them from touching each other or any metal while the pack is still on. Doing it in this order avoids sparks and keeps everything safe. Then let the car run or drive it a good while so the alternator recharges the battery — remember, a jump only starts the car; it does not refill the battery.

TIP**19. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech**

After any jump, drive for at least twenty or thirty minutes, or put the battery on a charger.

Shutting the car right off again may leave you stranded a second time. SAFETY RULE 27. No Sparks Near a Battery The one rule that prevents a bang. I will say it plainly because it is the most important safety point in this whole guide: keep sparks and flames away from a battery. When a battery charges or gets jumped, it can release hydrogen gas, which is flammable. A stray spark from clamps touching, a cigarette, or a flame can ignite that gas and, in rare cases, crack the battery open and spray acid. This is exactly why you ground a jump clamp away from the battery, work with the car and chargers off, and never smoke under the hood. Respect it and you will be perfectly safe. I bring up the no-spark rule so often because it is the one mistake that turns a routine job into a trip to the emergency room, and it is completely avoidable. The gas a battery can give off is invisible and odorless, so you will never know it is there. That is exactly why the habit matters: no flames, no cigarettes, no touching the clamps together, and ground the jump clamp away from the battery, every single time, whether or not you think any gas is present. Make the safe way your only way and you simply never have to worry about it. No smoking, flames, or sparks near a battery. Ground the black jump clamp away from the battery. Connect and disconnect with chargers and the car switched off. Wear eye protection when working close to a battery. EXTRAS 28. The Handy Extras on a Jump Pack More than just starting a car. One reason I like jump packs is that they double as a little toolbox. Most have USB ports to charge a dead phone — worth a lot if you are stuck somewhere with no signal and a flat phone. Many include a bright LED flashlight, often with an emergency blink mode, for a roadside at night. Some bigger ones even have an air compressor built in to pump up a low tire. So the pack you bought to start the car also covers a dead phone, a dark night, and a soft tire. That is a lot of peace of mind in a small box.

GOOD TO KNOW

20. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

Because the pack also charges phones, it slowly drains faster if you use it that way. Check and top up the charge more often if you lean on the USB ports. CABLES VS PACK 29. Jumper Cables or a Jump Pack? Both work; one needs a good Samaritan. Traditional jumper cables still work fine, but they need a second running car and someone willing to stop and help. On an empty rural road that may be a long wait. A jump pack needs no one — you rescue yourself. I suggest carrying both if you can: the pack for independence and the cables as a backup or to help someone else. If you only keep one, make it the jump pack, since it does not depend on a stranger showing up. Just remember the pack only helps if it is charged. Traditional jumper cables still work, but they come with a catch: you need a second running car and a willing stranger to use them, and on an empty rural road that help can be a long time coming. A jump pack needs no one; you rescue yourself. If you can, carry both, the pack for independence and the cables as a backup or to lend a hand to someone else. If you only keep one thing in the trunk, make it the jump pack, since it never depends on another driver happening along at the right moment. Jumper cables Jump pack Needs a second car Yes No Needs charging No Yes, keep it topped up Charges your phone too No Usually yes

WINTER KIT

21. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

30. A Simple Winter Car Kit Pair the pack with a few basics. Since we are talking cold-weather starting, let me round out the trunk. Alongside your charged jump pack, a small winter kit makes an Ohio breakdown far less miserable: a blanket, gloves, a flashlight with fresh batteries if your pack's light is not enough, a bit of sand or cat litter for traction, an ice scraper, and some water and a snack. None of it is expensive, and on a cold night miles from town it is the difference between an inconvenience and a scary situation. The jump pack is the hero, but a blanket keeps you comfortable while it works. A charged jump pack, checked before winter. A warm blanket and gloves. A flashlight, an ice scraper, and traction sand or litter. Water and a snack, in case you wait a while. SEASONAL 31. Storing a Vehicle for the Season Put it away right, start it up easy. If you tuck a vehicle away for months — a convertible for winter, a motorcycle, an RV — a little prep means it starts easily come spring. Hook up a maintainer so the battery stays full, or if there is no outlet, disconnect the negative cable so parasitic drain cannot flatten the battery while it sits. Store it out of extreme temperatures if you can, park it clean and dry, and if you disconnected the battery, remember you will need to reset the clock and radio when you reconnect it. A maintained battery comes back to life; a neglected one often needs replacing. TIP No power where the vehicle is stored? Disconnecting the negative cable is the simple fallback. It stops the slow drain, so the battery is still good when you reconnect it.

RECAP

22. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

32. The Short Version Everything above, boiled down. Here is the whole guide in a handful of lines. Your 12-volt battery lasts three to five years and warns you with slow cranking, dim lights, and clicking before it quits. Cold weather and a diet of short trips wear it out fastest. Keep the terminals clean, put a maintainer on anything that sits, and get a free test at the parts store when in doubt. Carry a charged lithium jump pack sized to your engine, keep it out of extreme heat and cold, and always keep sparks away from any battery. Three to five years; watch for slow cranking and clicking. Cold and short trips are hardest on a battery. Clean terminals with baking soda, negative cable off first. Maintainer for stored vehicles; free test at the parts store. Charged jump pack, sized to your engine, no sparks ever near a battery. GET HELP 33. When to Call Bill Happy to sort it out in the driveway. If any of this feels like more than you want to tackle — cleaning crusty terminals, hooking up a maintainer the right way, figuring out whether your battery is dying or just drained, or learning to use a new jump pack — give me a call. I am Bill, and in more than thirty years of in-home and driveway tech help around Portage County I have jumped, tested, and replaced more batteries than I can count. I will come to you, show you how it all works at your own pace, and make sure you feel confident doing it yourself next time. Reach me at (330) 200-8042 and we will set up a visit. I can get your jump pack charged and show you the safe way to use it, put a maintainer on the car that sits, and leave you with a battery you can trust through the winter. No pressure, and my friendly guarantee is behind every visit. Sophie can help you find a time that works. TIP Heading into winter with a battery that is three or four years old? Call and we will test it in your driveway before the first cold snap leaves you stranded.

CHEAT SHEET

23. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

Everyday Cheat Sheet Keep this page handy. It points you straight to what to do for each task. I want to... Do this I want to... Do this Know if my battery is weak Watch for slow cranking, dim dash, and clicking Make it last longer Take longer drives and keep terminals clean Clean corrosion Baking soda and water, negative cable off first Keep a parked car's battery up Hook up a maintainer (trickle charger) Get it tested free Stop by an auto-parts store Carry a backup Keep a charged lithium jump pack in the car Get a hand with any of it Call me at (330) 200-8042 Get help Call Bill: (330) 200-8042

HOW I CAN HELP

24. For electrical, gas, water, or ladder work, please call a licensed professional. — Bill's Home Tech

Your Visit — and My Promise In-home visit — \$99 flat for your first visit. No contracts and no surprise charges, and a 30-day follow-up is included. Remote Support — \$49 for a screen-share session. I only connect with your permission, you watch the whole time, and you can end anytime. If I can't fix it over the screen-share, I refund the \$49 — and if it turns out you need me in person, that \$49 goes toward your visit. It's included free for Support Plan members (\$39/mo). GOOD TO KNOW My promise — If you're not 100% satisfied with your visit, I'll come back at no charge, or refund the full \$99. No questions, no awkwardness. That's how I'd want to be treated. Call or text (330) 200-8042 · Book a visit: billshometech.com/book · bill@billshometech.com This free guide is for general information only — not professional advice, and no substitute for your device's own manual. Any prices or outside products mentioned can change; please confirm current details before you buy. Please use your own good judgment and follow it at your own risk — for anything involving electricity, gas, water, or heights, stop and call a licensed professional. Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results. © 2026 Bill's Home Tech, LLC.

AT A GLANCE

A Picture to Follow Along

If the car won't start

Work through it calmly, in this order.




Illustration — a schematic. The order is a suggestion; do one box at a time.

A schematic of the plan — company steps vary; the order does not have to.

AT A GLANCE

A Second Look

What shortens battery life

Four things that wear a battery down.




Illustration — a schematic. Set-up screens differ; each takes only a few minutes.

BEFORE YOU GO

A Note From Bill

A quick note from Bill. I write these guides to make home tech a little less frustrating, and I do my best to keep every step accurate and up to date. Still, every home, device, and setup is a bit different, so I can't promise a guide will match yours exactly or fix your particular problem. These guides are for general information only — they're not professional, legal, or financial advice, and they don't replace your device's own manual or the manufacturer's instructions. Please go slow, use your own good judgment, and use everything here at your own risk. If a step involves electrical wiring, a gas appliance, a water heater, plumbing, or climbing a ladder — or if anything just doesn't feel safe — please stop and call a licensed professional (or give me a call at 330-200-8042). Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results.



HOW I CAN HELP

Your Visit — and My Promise

In-home visit — \$99 flat for your first visit. No contracts and no surprise charges, and a 30-day follow-up is included.

Remote Support — \$49 for a screen-share session. I only connect with your permission, you watch the whole time, and you can end anytime. If I can't fix it over the screen-share, I refund the \$49 — and if it turns out you need me in person, that \$49 goes toward your visit. It's included free for Support Plan members (\$39/mo).

GOOD TO KNOW

My promise — If you're not 100% satisfied with your visit, I'll come back at no charge, or refund the full \$99. No questions, no awkwardness. That's how I'd want to be treated.

Call or text **(330) 200-8042** · Book a visit: **billshometech.com/book** · **bill@billshometech.com**

This free guide is for general information only — not professional advice, and no substitute for your device's own manual. Any prices or outside products mentioned can change; please confirm current details before you buy. Please use your own good judgment and follow it at your own risk — for anything involving electricity, gas, water, or heights, stop and call a licensed professional. Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results. © 2026 Bill's Home Tech, LLC.