BILL'S HOME TECH

Home & Small Business Tech Solutions

AN EXTENDED GUIDE · NO. 2368

Updated November 2026

Dead Zones in One Room — Extend Coverage

Why one room's Wi Fi goes dark, the free fixes to try first, and mesh vs. extender made clear

Plain-English home-network help from:

Bill's Home Tech

Portage County, Ohio

Tech Made Simple. Service Made Personal.

Bill Davis — Bill's Home Tech

(330) 200-8042 · bill@billshometech.com · Atwater, Ohio

Book a visit · billshometech.com/book

What's Inside

Everything in this guide, with page numbers. Skip to whichever chapter answers your question right now.

The 60-Second Version 3

The Short Version 3

Why One Room Goes Dark 4

Map Your Dead Zones First 4

Fix One: Move the Router 5

Fix Two: Clear What's in the Way 6

When Free Fixes Aren't Enough: Your Two Options 6

Why Mesh Usually Wins 7

Buying the Right Mesh for Your Home 8

Placing Mesh Units So They Actually Help 8

What About an Extender? When It's Fine 9

Set It and Keep It Working 10

When to Call Bill 10

Everyday Cheat Sheet 12

A Note From Bill 13

Your Visit — and My Promise 14

SUMMARY

The 60-Second Version

A dead zone is about where your signal can reach, not how fast your internet is. First, map it: run a speed test in each room. Then try the free fix — move the router to a central, open, elevated spot, out of cabinets and away from metal and mirrors.

If a room is still weak, add coverage. For most homes a mesh system (two or three matching units acting as one network) is the lasting fix and beats a cheap extender, which copies a weak signal and makes a confusing second network name. Place mesh satellites about halfway to the dead zone so each can still hear the main unit clearly.

1 The Short Version

There is one room — the back bedroom, the sunroom, the far end of the porch — where the Wi Fi goes to die. Video buffers, pages hang, and your phone shows one lonely bar. Everywhere else is fine. That is a "dead zone," and it is one of the most fixable problems in the whole house once you understand that it is about where your signal can reach, not how good your internet is.

This guide walks you from the free fixes — moving the router, clearing what blocks the signal — up to the two real tools for stretching coverage: a mesh system and an extender. We will be honest about which is worth your money, because for most homes one of them is clearly the better buy.

- A dead zone is a coverage problem — the signal cannot reach that room, not that your internet is slow.
- Start free: move the router into the open and higher up before buying anything.
- Walls, floors, metal, and distance are what eat your signal.
- To truly extend coverage, a mesh system beats a cheap extender in almost every home.

TIP

Before spending a dollar, just try moving your router. Getting it up off the floor, out of a cabinet, and into a central open spot fixes a surprising number of dead zones on its own — the signal was being smothered, not stretched too thin.

2 Why One Room Goes Dark

Wi Fi is a radio signal, and like any radio it gets weaker with distance and with every obstacle it has to pass through. Your router sits in one spot and sprays signal outward in all directions, including uselessly into the yard and up into the attic. By the time it reaches a far room — especially through a couple of walls — there may be barely enough left to work with.

Some materials are far worse than others. Plain drywall is gentle on a signal; brick, stone, tile, mirrors, and anything metal are brutal. A big appliance, a metal file cabinet, a fish tank, or even a wall with pipes and ductwork in it can throw a shadow that leaves the room behind it dark. Knowing this is half the battle, because it tells you whether to move the router or to add coverage.

GOOD TO KNOW

Water absorbs Wi Fi, which is why a signal struggles to pass through a full fish tank, a water heater, or even a crowded room full of people. It is also why signal can seem worse in a humid sunroom. None of this is a fault — it is just physics, and it is why placement matters so much.

3 Map Your Dead Zones First

Before changing anything, spend five minutes learning the real shape of your coverage. This turns guesswork into a plan and shows you exactly where help is needed.

1. On your phone, open a speed test app or site like Fast.com.
2. Stand next to the router and run it — that is your best case number.
3. Walk to each room, run the test again, and jot the number down on a rough sketch of your home.
4. Mark the rooms where the number drops sharply or the signal bars fall — those are your dead zones.

> **TIP**
>
> Note where the number falls off a cliff versus where it just gently fades. A sudden drop usually means a specific obstacle (a wall, an appliance) you can work around; a gradual fade across the house means you simply need more coverage reaching farther out.

4 Fix One: Move the Router

The single most powerful free fix is to put the router in a better spot. Routers are often shoved wherever the internet cable happens to enter the house — a corner, a basement, a closet — which is the worst place for even coverage.

1. Move the router as close to the center of your home as the cable allows.
2. Raise it up — on a shelf or desk, not on the floor — so the signal spreads out over furniture, not under it.
3. Pull it out of any cabinet, drawer, or closet; closed doors and wood shrink the signal.
4. Point any external antennas up, and keep the router a few feet from the TV, microwave, and cordless phone base.
5. Re run your room by room test to see what improved.

> **WATCH OUT**
>
> If the internet cable only reaches a far corner, you are not stuck — a longer cable, or a small job to add an outlet in a better spot, can relocate the router centrally. That relocation alone sometimes erases the dead zone and saves you buying any extra gear.

5 Fix Two: Clear What's in the Way

Sometimes the router is fine but something specific is standing between it and the dark room. A little rearranging can reopen the path.

- Move large metal objects (filing cabinets, metal shelving, the refrigerator's back) out of the direct line.
- Keep the router away from other radios — microwaves, baby monitors, and older cordless phones all share its airspace.
- If a mirror or a fish tank sits between the router and the room, the signal is being bounced or absorbed; reroute around it.
- Close the gap through just one wall rather than three — even shifting the router to the near side of a central wall helps.

> **GOOD TO KNOW**
> Microwaves and the 2.4GHz Wi Fi band use almost the same airspace, which is why some people see their far room video stutter every time the microwave runs. It is harmless and temporary, but it is a real clue that the room is relying on a thin signal.

6 When Free Fixes Aren't Enough: Your Two Options

If you have moved the router into the open and the far room is still weak, the signal simply cannot stretch that far through your home, and it is time to add coverage. There are two kinds of product for this, and the difference between them matters more than almost anything else in this guide.

	Extender	Mesh system
What it does	Rebroadcasts a copy of your existing Wi Fi	Replaces your Wi Fi with a team of units that act as one

Network name	Often a second name (e.g. "MyWiFi_EXT")	One name everywhere — you never switch
Roaming room to room	Can drop and need reconnecting	Seamless hand off as you walk
Best for	One small nearby gap, tight budget	Whole home coverage, the lasting fix

> *For most homes with a real dead zone, a mesh system is the fix that actually lasts; an extender is a patch.*

Rather not do this yourself? I'll come to your home and set it up for you — a flat $99 first visit across Portage County, Ohio and nearby communities. Outside the area? I also help remotely by phone or screen-share. Book at billshometech.com/book or call (330) 200-8042.

7 Why Mesh Usually Wins

A mesh system is a set of two or three matching units you place around the house. They talk to each other and present your devices with a single, seamless network, so as you carry your phone from the kitchen to the back bedroom it hands off automatically to the nearest unit without you noticing. There is one network name and one password everywhere.

An extender, by contrast, grabs the weak signal that already reached the far area and rebroadcasts it — often cutting the speed in half and creating a second network name you have to remember to switch to. For a single dead spot right at the edge of good coverage it can be a cheap patch, but in most homes it trades one annoyance for another.

GOOD TO KNOW

Mesh systems have come down in price and are genuinely easy to live with. If your dead zone is a room you use every day — a home office, a bedroom where you watch TV — the smoother experience of mesh is almost always worth it over a bargain extender.

8 Buying the Right Mesh for Your Home

You do not need the most expensive system; you need the right size and a few sensible features. Here is how to choose without overspending.

- Match the number of units to your home: a 2 unit kit for a modest house, a 3 unit kit for a larger or multi story one.
- Look for a current standard — a system described as Wi Fi 6 or newer is a safe, future proof choice.
- Buy a kit from one maker rather than mixing brands, so the units cooperate properly.
- If you have fast internet, check that the mesh can keep up; a very cheap kit can become the new bottleneck.

WATCH OUT

Picking a mesh system is one of those choices where a five minute conversation saves you from buying too much or too little. I'm happy to steer you to the right size for your home and your internet speed before you spend anything — and to set it up so it just works.

9 Placing Mesh Units So They Actually Help

A mesh system only works as well as its placement. The satellite units need to sit where they can still hear the main unit clearly while reaching into the dead zone — a middle ground, not buried in the far corner.

1. Place the main unit where your internet comes in, out in the open and up high.
2. Put the second unit about halfway between the main unit and the dead zone, not inside the dead zone itself.
3. Keep each unit in open air — off the floor, out of cabinets, away from big metal objects.
4. Use the system's app to check the connection strength between units and nudge them until it reads strong.

WATCH OUT

A common mistake is to shove the satellite unit right into the weak room. If it cannot hear the main unit well from there, it just rebroadcasts a weak signal. It needs a clear line back to the main unit — think stepping stones across a stream, evenly spaced.

10 What About an Extender? When It's Fine

Extenders are not evil — they are just the wrong tool for a true whole home coverage problem. There are a few narrow cases where a single extender is a perfectly sensible, inexpensive choice.

- One nearby spot, like a garage or a porch just past good coverage, where you only need light use.
- A tight budget where any improvement beats none and you do not mind a second network name.
- A rental where you cannot rework the setup and just need a temporary boost.

GOOD TO KNOW

If you do use an extender, place it halfway between the router and the weak area — somewhere that still has a solid signal to copy. Putting it where the signal is already dying only rebroadcasts a dying signal.

11 Set It and Keep It Working

Once coverage reaches every room, a little upkeep keeps it that way and prevents the dead zone from quietly creeping back.

- Leave the mesh units where they test strong — resist moving them to "tidy up."
- Let the system update itself; mesh makers push improvements that you want.
- Re run your room test after rearranging furniture or adding a big appliance.
- If a unit goes offline, a simple power cycle (unplug 30 seconds, plug back in) usually revives it.

> **GOOD TO KNOW**
>
> Coverage can change when your household does — a new big screen TV, a metal shelving unit, even a full bookcase on an interior wall can nudge a borderline room back toward dark. A quick re test now and then catches it early.

12 When to Call Bill

Mapping dead zones and moving a router is well within reach for most people, and it is a great first thing to try. But choosing between mesh and extender, picking the right system for your home, and placing the units so they genuinely cooperate is where a little experience pays for itself many times over.

I come to you, map your coverage properly, and tell you honestly whether moving the router is enough or whether mesh is worth it — and if it is, I set it up and place every unit so the whole house just works, with one network name you never have to think about again.

- You have tried moving the router and a room is still dark.
- You are about to buy mesh or an extender and want to spend once, correctly.
- Your current extender created a confusing second network you keep having to switch to.
- You want strong, seamless Wi Fi in every room without the trial and error.

CHEAT SHEET

Everyday Cheat Sheet

Keep this handy. Try the free fixes before buying anything.

I want to...	Do this...
Find my dead zones	Run Fast.com in each room; note where the number drops
Fix it for free	Move the router central, up high, out of cabinets and off the floor
Clear the path	Move metal objects, mirrors, and fish tanks out of the signal's way
Extend coverage the right way	Add a mesh system — one network name across the whole home
Place mesh units	Put a satellite halfway to the dead zone, not inside it
Consider an extender	Only for one small nearby spot on a tight budget
Get help	Call Bill: (330) 200-8042

BEFORE YOU GO

A Note From Bill

A quick note from Bill. I write these guides to make home tech a little less frustrating, and I do my best to keep every step accurate and up to date. Still, every home, device, and setup is a bit different, so I can't promise a guide will match yours exactly or fix your particular problem. These guides are for general information only — they're not professional, legal, or financial advice, and they don't replace your device's own manual or the manufacturer's instructions. Please go slow, use your own good judgment, and use everything here at your own risk. If a step involves electrical wiring, a gas appliance, a water heater, plumbing, or climbing a ladder — or if anything just doesn't feel safe — please stop and call a licensed professional (or give me a call at 330-200-8042). Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results.

HOW I CAN HELP

Your Visit — and My Promise

You don't have to remember all of it — just that a friendly, patient person is one call away, whenever you'd rather have a hand.

KEY SPECS

In your home — $99 flat for the first visit, no contracts and no surprises, with a 30-day come-back-free follow-up. In-home visits cover Portage County, Ohio and nearby communities.
Outside the area? Remotely — $49 for a screen-share session (free for Support Plan members, $39/mo), refundable if I can't fix it — and credited toward a visit if you'd rather have me in person. Book either at billshometech.com/book.

GOOD TO KNOW

My promise — If you're not 100% satisfied with your visit, I'll come back at no charge, or refund the full $99. No questions, no awkwardness. That's how I'd want to be treated.

Whenever you're ready, I'll come to your home anywhere in Portage County, Ohio and nearby communities, at your pace. Too far for a house call? I also help remotely. Book at billshometech.com/book or call (330) 200-8042. — Bill

Call or text (330) 200-8042 · bill@billshometech.com

This free guide is for general information only — not professional advice, and no substitute for your device's own manual. Any prices or outside products mentioned can change; please confirm current details before you buy. Please use your own good judgment and follow it at your own risk — for anything involving electricity, gas, water, or heights, stop and call a licensed professional. Bill's Home Tech and Bill Davis can't be responsible for any damage, data loss, or injury that results. © 2026 Bill's Home Tech, LLC.