BILL'S HOME TECH
Home & Small Business Tech Solutions

BILL'S COMPLETE MANUALS

Rural Property Security

Driveway alarms, barn cameras, long-range Wi-Fi and power outages — explained in plain English, one step at a time

A plain-English guide for farms, long driveways and country homes

Take your time — you can't break it

Written for you by Bill — Bill's Home Tech

(330) 200-8042 · BillsHomeTech.com

For driveway alarms, cellular & Wi-Fi cameras and rural internet · facts current November 2026

What's Inside

This is your guide to keeping an eye on a country property: the long driveway, the gate, the barn, the shed down the lane and the house itself. Read it in any order and at your own pace. Each chapter explains what a gadget actually does *for you*, what it costs, and how to set it up safely, step by step. Brand names appear only as examples so you know what to look for, not as recommendations. Prices and plans were checked in November 2026 and change often, so confirm them on the maker's own website before you buy.

Part 1 — Getting Started

1 A Note from Bill
2 What Makes Rural Security Different
3 Walk Your Property First
4 Choosing Your Building Blocks

Part 2 — Driveway & Gate Alerts

5 Driveway Alarms Explained
6 Setting Up a Motion Driveway Alarm
7 Magnetic Probe Alarms: Vehicles Only
8 Sensors for Gates, Barns & Sheds
9 Long-Range Sensors (LoRa) Like YoLink

Part 3 — Cameras for Barns, Sheds & Long Driveways

10 Picking Camera Spots on a Farm or Big Lot
11 Wi-Fi Cameras Beyond the House
12 Cellular (LTE) Cameras
13 Cellular Camera Data Plans
14 Trail-Camera Style Options

Part 4 — Getting Internet to the Outbuildings

15 Why Wi-Fi Fades Out by the Barn
16 Mesh Wi-Fi & Outdoor Access Points
17 Point-to-Point Wireless Bridges
18 Buried Cable vs Going Wireless

Part 5 — Power: Solar, Batteries & Outages

19 Battery & Solar Cameras
20 When the Power Goes Out
21 Ladders, Wiring & Weather: Safe Installation

Part 6 — Living with Limited Internet

22 Starlink, Fixed Wireless & Other Rural Internet
23 Cameras on a Slow or Capped Connection
24 Recording Locally vs the Cloud

Part 7 — Animals, Neighbors, the Law & Scams

25 Taming False Alarms: Deer, Livestock & Weather
26 Privacy, Trespass & Being a Good Neighbor
27 Scams Aimed at Rural Homeowners

Part 8 — When to Call Bill & Your Cheat-Sheet

28 When to Call Bill
29 Your Rural Security Cheat-Sheet

PART 1

Getting Started

Why a country property needs a different plan than a house in town, how to walk your land and decide what matters, and the building blocks you'll choose from. Start here.

CHAPTER 1

A Note from Bill

Hello, and welcome. If you live at the end of a long gravel driveway, keep equipment in a pole barn, have a shed or a workshop out past the garden, or simply can't see the road from your kitchen window, this guide is for **you**. Maybe you'd like to know when a car turns in. Maybe you'd sleep better with a camera on the barn door. Maybe a grown child who lives far away would worry less if they could check in.

I'm Bill. I bring more than 30 years of professional experience to helping folks here in Portage County feel at home with their technology, and a lot of Portage County is rural: farms, wooded lots, long lanes and outbuildings a few hundred feet from the house. Most security advice is written for a front porch in a subdivision. This guide is written for the barn, the gate and the far end of the driveway.

WHAT THIS DOES FOR YOU

What this guide does for you

By the end you'll know which tool fits each job: a simple driveway alarm that chimes in the kitchen, a sensor on the barn door, a camera that works with no Wi-Fi at all, or a wireless link that carries your internet to the shop. You'll know what each costs every month, what happens when the power goes out, and how to keep deer and cattle from setting everything off.

You can't break it by exploring

You can't hurt a camera app or a sensor by tapping around in its settings. Every setting can be changed back. The places to slow down are real ones, and I'll flag each: **ladders**, **electrical wiring**, **digging**, and anything that asks for **money or a contract**.

What's in this guide

- **Planning**: what makes rural security different and how to map your property (Part 1).
- **Driveway and gate alerts**: motion alarms, magnetic probes, door sensors and long-range sensors (Part 2).
- **Cameras** for the barn and the lane, including cellular cameras that need no Wi-Fi (Part 3).
- **Getting internet to the outbuildings**: mesh, outdoor access points and wireless bridges (Part 4).
- **Power**: solar, batteries, outages and safe installation (Part 5).

- **Limited internet**: Starlink, fixed wireless and recording locally (Part 6).
- **Animals, neighbors, the law and scams** (Part 7).

You're never stuck alone

If you get stuck, call me at **(330) 200-8042**. No question is too small. Let's start by looking at what makes a country property different.

— Bill

CHAPTER 2

What Makes Rural Security Different

A camera kit from the big-box store is designed for a house on a quarter-acre lot, where the Wi-Fi reaches everything and the power rarely goes out. Out in the country, five things change the picture.

1. Distance

Your driveway may be longer than a Wi-Fi signal can travel. The barn may be 300 feet from the router, with trees and metal siding in between. Anything that needs to "talk" to the house has to cover that distance, so range is the first thing to check on any product.

2. Internet that's slow, capped or missing

Many rural homes rely on satellite (such as Starlink), fixed wireless from a tower, or a cellular hotspot. These can work well, but some have slower **upload** speeds (sending video *out* of the house) or monthly data limits. Cameras that stream all day can eat into both. Part 6 covers how to live with that.

3. Power that comes and goes

Storms knock out rural power lines more often, and it can take longer to restore. A camera system that goes dark the moment the power fails isn't much comfort. Part 5 explains batteries, solar and backups.

4. Animals

Deer, coyotes, raccoons, barn cats, dogs, horses and cattle all set off motion sensors. Without some thought, your phone will buzz all night and you'll learn to ignore it, which defeats the purpose. Chapter 25 is all about taming false alarms.

5. Nobody nearby to notice

In town, a neighbor might see a strange truck. In the country, your property may go unwatched for hours. That's why an early warning (a chime when a vehicle turns in, or a text when the barn door opens) is often more useful than hours of recorded video.

WHAT THIS DOES FOR YOU

What this means for you

You don't need the fanciest camera. You need the right *mix*: something that warns you early, something that records what happened, and a way to get the signal and power to where it's needed.

CHAPTER 3

Walk Your Property First

Before buying anything, take a slow walk around your property with a notepad, or sketch it at the kitchen table. Ten minutes of planning saves a lot of returned boxes.

Draw a simple map

1. Draw the house, the driveway from the road, and every outbuilding: barn, garage, shed, shop, well house, coop.
2. Mark where your internet comes in and where the router sits.
3. Mark every outdoor electrical outlet and any building that has power.
4. Pace off (or estimate) the distance from the house to the road and to each building. A normal walking stride is roughly two and a half feet, so 40 steps is about 100 feet.
5. Note what's in between: trees, hills, metal buildings, grain bins.

Decide what you're protecting

Write down, in plain words, what you want to know about. For example:

- "I want a chime in the house when a car or truck turns in the driveway."
- "I want a text if someone opens the barn or the gas pump shed."
- "I want to see who came by while we were at church."
- "I want to know if the well house gets cold enough to freeze."
- "My son in Columbus wants to check on things when we travel."

> **TIP**
>
> **Alerts first, video second**
>
> On a big property, the most useful thing is usually an **alert** at the right moment, with a camera pointed at the same spot so you can see what caused it. Plan both together.

Check your phone signal at each spot

Walk to the end of the driveway and to each building with your phone and look at the bars. Try loading a web page with Wi-Fi turned off. If your phone gets a usable cellular signal there, a cellular camera (Chapter 12) will probably work there too. Write down which carrier you have.

STAY SAFE

Walk it in daylight

Do this walk in daylight, on good footing, with your phone in your pocket. Watch for livestock, electric fence wires and uneven ground near the ditch.

CHAPTER 4

Choosing Your Building Blocks

Almost every rural setup is built from the same handful of pieces. Here they are side by side, so you can match each one to a line on your map.

Building block	What it's good for	Needs internet?	Monthly cost
Driveway alarm (motion or probe)	A chime or handheld beep when someone comes up the lane.	No	None
Long-range sensors (LoRa type, like YoLink)	Phone alerts for doors, gates, temperature, water, far from the house.	Yes, at the hub	Usually none
Wi-Fi camera	Video near the house or where Wi-Fi reaches.	Yes	Optional plan
Cellular (LTE) camera	Video where there's no Wi-Fi but a phone signal.	No (uses cellular)	Data plan required
Cellular trail camera	Photos or short clips from the woods or a far gate.	No (uses cellular)	Plan required
Wireless bridge	Carries your home internet to a barn or shop.	Uses yours	None

Three common mixes

The simple setup

A battery driveway alarm with a chime in the kitchen, plus a Wi-Fi doorbell or camera at the house. No monthly cost for the alarm, and it works even if the internet is down.

The barn-and-lane setup

A driveway alarm, a door sensor on the barn, and one cellular camera at the gate or barn. Good when the outbuildings are out of Wi-Fi range.

The connected farm

A wireless bridge carries internet to the barn, where a regular outdoor camera and access point give you Wi-Fi there too. More work up front, but no per-camera data plans.

HEADS UP

Count the monthly costs before you buy

Every cellular camera needs its own data plan, and many camera brands sell optional cloud plans on top. Add them up for a full year before deciding. The Camera Subscriptions guide in this series goes deeper on cloud plans.

GOOD TO KNOW

Related guides

If most of your cameras will be on the house itself, the Ring, Outdoor & Floodlight Cameras, and Reolink & Wired Camera Systems guides in this series cover them in detail. This guide focuses on everything farther out.

PART 2

Driveway & Gate Alerts

Simple alarms that chime in the house when someone turns in, sensors for gates and barn doors, and long-range sensors that reach far past your Wi-Fi.

CHAPTER 5

Driveway Alarms Explained

A **driveway alarm** is a small sensor you mount beside the driveway and a **receiver** you keep in the house. When something passes the sensor, the receiver chimes or beeps. Most work by radio, directly from sensor to receiver, with no Wi-Fi, no internet and no monthly fee.

WHAT THIS DOES FOR YOU

What it does for you

You hear a chime a minute or two before someone reaches the house. That's time to look out the window, put the dog in, or simply not be startled by a knock. It also tells you when the mail carrier or a delivery truck has come and gone.

The three main kinds

Type	How it works
Motion (PIR) sensor	Senses body heat moving across its view. Easy to install on a post. Detects people, cars and animals alike.
Magnetic probe	A probe buried beside the driveway senses the large metal mass of a vehicle passing. Ignores people and animals. More digging to install.
Beam (infrared)	Two posts on either side of the drive; an invisible beam is broken when something passes. Less common on long rural drives.

GOOD TO KNOW

What "PIR" means

PIR stands for **passive infrared**. It's the same kind of sensor that turns on a motion light. It notices a warm shape moving against a cooler background, which is why it can't tell a deer from a person.

Range: read the fine print

Driveway alarm boxes advertise ranges like "500 feet" or "a quarter mile" or even several miles. Those figures are measured in open air with a clear line of sight. Trees, hills, metal buildings and walls all shorten the real range. Buy a kit rated comfortably longer than your driveway, and test it before you mount anything permanently (Chapter 6).

Receivers

- **Plug-in or tabletop chime**: sits in the kitchen; some have volume and tone settings.
- **Handheld receiver**: like a walkie-talkie you carry to the garden or the shop.
- **Several sensors, one receiver**: many kits let you add sensors and give each a different tone, so you know whether it was the driveway or the barn lane.

TIP

Keep a spare set of batteries

Most driveway sensors run on batteries. Note the type and the date you changed them on the cheat-sheet in Chapter 29, and keep spares in the kitchen drawer.

CHAPTER 6

Setting Up a Motion Driveway Alarm

A motion driveway alarm is the easiest place to start. Here's how to place it so it catches vehicles and skips most of the wildlife.

Test before you mount

1. Put fresh batteries in the sensor and plug in or power up the receiver in the room where you'll keep it.
2. Pair them if the instructions say to (often by pressing a button on each within a short time).
3. Have someone carry the sensor to the spot you have in mind and wave a hand in front of it.
4. Listen for the chime in the house. Try a few spots if it's unreliable.
5. Only then mount it permanently.

Where to put the sensor

- **Far enough from the road** that passing traffic doesn't trigger it. Many people put it a little way up the driveway, past the mailbox.
- **Aimed across the driveway** at an angle, not straight down it, so a vehicle crosses its view.
- **At about bumper height**, so it sees cars and trucks more easily than small animals. The kit's instructions give the recommended height for that model.
- **Away from bushes and tall grass** that sway in the wind and warm up in the sun.
- **Not facing the rising or setting sun** where possible, since strong sunlight can cause false alerts.

TIP

Two sensors tell you direction

With two sensors a short way apart and different chime tones, you can tell whether someone is coming in or going out by which tone sounds first.

Choosing a model

Popular battery kits (Guardline is one widely sold example) bundle a sensor and receiver and let you add more of either. Look for: a range rated well beyond your driveway's length, weatherproof sensors, adjustable sensitivity, and a receiver with volume control. Check that extra sensors are compatible with your receiver before ordering; some makers sell separate long-range lines that don't mix.

HEADS UP

Mow and trim around it

Tall weeds blowing in front of a motion sensor are the most common cause of false alarms. Keep a clear patch in front of it through the summer.

CHAPTER 7

Magnetic Probe Alarms: Vehicles Only

If deer and dogs keep setting off a motion sensor, a **magnetic probe** alarm is the classic farm answer. The probe is a sealed tube buried beside the driveway. It senses the disturbance a large metal object (a car, truck or tractor) makes as it passes, and a transmitter sends the alert to the house.

WHAT THIS DOES FOR YOU

What it does for you

Far fewer false alarms. A probe won't chime for a deer, a person on foot, or the barn cat. That makes it trustworthy: when it sounds, a vehicle really did turn in.

What to know before buying

- **It won't detect people on foot** (or most bicycles). Pair it with a camera or motion light if that matters.
- **Installation means digging** a shallow trench beside the driveway for the probe and its cable. The transmitter sits in a weatherproof box on a nearby post.
- **Long-range models** use stronger radios. Some, such as Dakota Alert's MURS line, use the Multi-Use Radio Service and advertise ranges measured in miles under ideal conditions.

About MURS radios

MURS is a set of radio channels the FCC sets aside for short-range personal and business use. The FCC licenses MURS "by rule": you don't need an individual license to use certified MURS equipment that follows the rules, including a two-watt power limit. Channels are shared, so you may occasionally hear or pick up other users nearby.

Installing a probe safely

1. Read the kit's instructions for probe depth and distance from the driveway edge.
2. **Call 811 a few days before you dig**. It's the free national "call before you dig" number; utility crews will mark buried lines.
3. Keep the probe away from culverts, fences and other metal that can confuse it.
4. Test by driving past slowly, then at normal speed, before you backfill the trench.

STAY SAFE

Don't dig blind

Rural properties often have buried electric lines to outbuildings, propane lines, and well and septic lines that aren't marked on any map. Call 811, and if you aren't sure where your own private lines run, dig gently by hand.

CHAPTER 8

Sensors for Gates, Barns & Sheds

A **contact sensor** is a two-piece gadget: one piece on the door or gate, one on the frame. When they separate, the sensor sends an alert. Inside the house these are common on alarm systems. On a farm they're just as useful on the barn door, the tack room, the fuel shed or a gate.

WHAT THIS DOES FOR YOU

What it does for you

Instead of walking down to check whether the barn is shut, your phone tells you the moment it opens, and the app shows whether it's open or closed right now.

Which sensors work at a distance?

Ordinary smart-home sensors (Wi-Fi, Zigbee or Z-Wave) usually reach only as far as a typical house. For an outbuilding a few hundred feet away, look for a **long-range** system built for it, such as the LoRa-based sensors in Chapter 9, or a driveway alarm kit that offers door sensors on the same receiver.

Fitting a sensor to a barn door or gate

1. Choose a weatherproof or outdoor-rated sensor if it will be exposed to rain, or mount it inside the door.
2. Close the door or gate and hold both pieces in place, lined up, within the gap the instructions allow.
3. Test it in the app: open and close a few times and confirm the status changes.
4. Fix it with screws or outdoor-rated mounting tape. Rough barn wood needs screws.
5. For a sliding barn door, mount the magnet on the door and the sensor on the frame so they meet when closed.

TIP

Gates that swing in the wind

A loose gate that rattles open and shut will flood you with alerts. Latch it properly, or use a vibration or tilt sensor that's less touchy, and set alerts only for certain hours.

Other handy sensors for outbuildings

- **Vibration sensors** on a toolbox, a gas tank or a trailer hitch.
- **Temperature sensors** in the well house, chicken coop or pump room to warn of freezing.
- **Water leak sensors** under a barn hydrant or water heater.
- **Motion sensors** inside the barn, where animals aren't, to catch someone walking in.

CHAPTER 9

Long-Range Sensors (LoRa) Like YoLink

LoRa (short for "long range") is a low-power radio technology that sends small messages a long way. YoLink is a smart-home brand built on it. Its sensors talk to a **hub** in the house, and the hub sends alerts to your phone through the internet.

How far it reaches

YoLink rates its hub-to-sensor range at up to **a quarter mile in open air**. The company notes that metal and other obstructions reduce it. A metal pole barn is the biggest obstacle on most farms, so test a sensor in its final spot before you rely on it, and expect less than the box says.

WHAT THIS DOES FOR YOU

What it does for you

One small hub in the house can cover the barn, the coop, the mailbox and the gate, without running Wi-Fi out there. Sensors run on batteries for a long time, so there's no wiring.

What you need

- A YoLink hub plugged in at the house and connected to your home internet.
- The free YoLink app on your phone.
- The sensors you want: door, motion, vibration, temperature, water leak, and others.

Setting up a sensor

1. Set up the hub first, following the app's instructions.
2. In the app, tap to add a device and scan the QR code on the sensor.
3. Give it a clear name, such as "Barn big door" or "Well house temp".
4. Take it to its final spot and check that the app shows it updating before you mount it.
5. Set the alerts you want (for temperature sensors, a high and low range; see the benefits chapter "Ways Your Rural Security Can Make Life Easier").

HEADS UP

The hub still needs internet

The sensors reach the hub by radio, but phone alerts travel over your home internet. If your internet or power is down, alerts to your phone stop. Chapter 20 covers backup power.

GOOD TO KNOW

Ranges are "up to"

Every long-range product, YoLink included, quotes its best case. Treat the number as a ceiling, not a promise. If a far sensor drops out, a second hub or moving the hub to a window facing the barn often helps.

PART 3

Cameras for Barns, Sheds & Long Driveways

Where to put cameras on a big property, how to get them online when Wi-Fi doesn't reach, what cellular cameras and their data plans really cost, and when a trail camera is the better fit.

CHAPTER 10

Picking Camera Spots on a Farm or Big Lot

On a large property you can't watch everything, and you don't need to. A few cameras at the right "choke points" tell you most of what you need to know.

The spots that matter most

- **Where the driveway leaves the road**: every vehicle has to pass it.
- **The main barn or shop door**, where the expensive equipment lives.
- **The gate or lane** into back fields, if equipment or livestock are out there.
- **The house's front and back doors** (a video doorbell covers one; see the Ring guide).
- **Fuel tanks or the gas pump**, if you have one on the farm.

WHAT THIS DOES FOR YOU

What it does for you

A camera at the end of the lane paired with a driveway alarm means the chime tells you *something* came in, and one tap on your phone shows you *what*.

Getting a useful picture

1. Mount cameras high enough to be out of easy reach, but low enough to see faces. Around 8 to 10 feet is a common compromise; check the camera's own instructions.
2. Aim at where a vehicle or person will be *close* to the camera, not at the far end of a field.
3. Angle slightly down and keep the sky out of most of the picture so it doesn't wash out.
4. Avoid pointing straight into the sunrise or sunset.
5. Look at the live view in daylight and again after dark before you call it done.

HEADS UP

License plates are hard

Most home cameras can't read a license plate on a moving vehicle at a distance, especially at night. If plates matter, put a camera where vehicles slow down (a gate or a curve) and aim it close and narrow.

Barns are hard on cameras

- **Dust and cobwebs**: wipe the lens with a soft cloth every so often. Spiders love the warmth of an infrared light at night.
- **Metal siding** blocks Wi-Fi and cellular signals. Mounting the camera outside the wall, or near a door or window, often helps.
- **Temperature**: check the camera's rated operating range for an unheated building in an Ohio winter.
- **Animals** chew cables. Run wires through conduit or out of reach.

CHAPTER 11

Wi-Fi Cameras Beyond the House

A Wi-Fi camera is the cheapest kind to run, with no data plan. The catch is that it needs a strong Wi-Fi signal where it's mounted, and home Wi-Fi rarely reaches far beyond the walls.

Test the signal before you mount

1. Stand where the camera will go, with your phone connected to your home Wi-Fi (not cellular).
2. Look at the Wi-Fi bars, then try playing a short video.
3. If it stalls or the bars drop to one, a camera there will struggle too.
4. Many camera apps also show a signal strength reading once the camera is installed; check it after a day.

TIP

Set it up in the house, then move it

With battery cameras, it's easier to do the app setup at the kitchen table, then carry the camera to its spot. If the live view becomes choppy out there, you've found the edge of your Wi-Fi.

When the signal is weak

Situation	Usually the answer
Barn or shed within 100–150 feet	A mesh Wi-Fi point or outdoor access point may be enough (Chapter 16).
Several hundred feet or more	A point-to-point wireless bridge (Chapter 17), or a cable (Chapter 18).
No practical way to bring Wi-Fi	A cellular camera (Chapter 12) or trail camera (Chapter 14).

HEADS UP

Upload speed matters too

A camera sends video *out* of your house. On satellite or fixed wireless with modest upload speed, several cameras streaming at once can slow everything else. Chapter 23 explains how to keep it in check.

2.4 GHz vs 5 GHz

Many routers broadcast two kinds of Wi-Fi. The **2.4 GHz** band travels farther and through walls better; the **5 GHz** band is faster but shorter-range. Many outdoor cameras use 2.4 GHz for exactly that reason. If your router lets you see both, the 2.4 GHz network is usually the one that reaches the yard.

CHAPTER 12

Cellular (LTE) Cameras

A **cellular camera** (also called an LTE or 4G camera) has a SIM card inside, like a cell phone. It sends alerts and video over the cell network instead of your Wi-Fi. If your phone gets a signal at the barn or the gate, a cellular camera can usually work there too, even with no internet at the house.

WHAT THIS DOES FOR YOU

What it does for you

You can watch a far gate, a hunting cabin, a rental field or a barn with no power and no Wi-Fi, as long as there's cell coverage. Paired with a solar panel, it can run on its own for a long time.

Examples of what's out there

Arlo, Reolink and others sell cellular models. Arlo's **Go 2**, for example, works over LTE or Wi-Fi. Arlo says it needs an activated SIM card with a mobile data plan, and lists AT&T, Cellcom, T-Mobile, U.S. Cellular and Verizon as compatible U.S. carriers. It can also record to a microSD card.

Reolink's cellular line (its "Go" family) is sold with Reolink's own data plans or works with a SIM from a supported carrier. The original Reolink Go has been discontinued; newer Go models replaced it.

Before you buy one

1. Check cell coverage **at the exact spot** with your phone (Chapter 3). One bar indoors may be two outside on a post, but no bars means no camera.
2. Find out which carriers the camera supports and which carrier is strongest at that spot. It may not be the one on your phone.
3. Decide where the data plan will come from: the camera maker, or a carrier (Chapter 13).
4. Plan power: a cellular camera usually runs on a battery, with an optional solar panel (Chapter 19).

TIP

Weak signal? Raise it

Height helps a cellular signal. A camera on a post or high on the barn often gets better reception than one mounted low. Some models also accept a larger external antenna; check the maker's accessories.

HEADS UP

One plan per camera

Each cellular camera needs its own SIM and plan. Three cellular cameras means three monthly bills. If you need several cameras in one building, a wireless bridge (Chapter 17) may cost less over time.

CHAPTER 13

Cellular Camera Data Plans

The camera is a one-time cost. The data plan goes on every month, so it's worth understanding what you're paying for.

How much data does a camera use?

That depends on how often it's triggered and how long it records. Arlo estimates the Go 2 uses roughly 700 MB to 2 GB a month. Reolink says that under normal use, about 2 GB a month should be enough for its cellular cameras, but watching live video is heavy: about 1 GB per hour of continuous live viewing at default settings on one model.

WHAT THIS DOES FOR YOU

What this means for you

A camera that records short clips when something moves can live on a small plan. A camera you watch live for an hour a day needs a much bigger one. Use live view for quick checks, not as a TV channel.

Where the plan comes from

Option	What to know
The camera maker	Some makers sell their own SIM plans. Reolink's U.S. price list in 2026, for example, started around $5.99 a month for 1 GB and $8.49 for 2 GB, with bigger plans and top-up packs available.
Your phone carrier	You may be able to add the camera to your existing plan as a data-only line. Ask about the monthly line fee and taxes, not just the data price.
A prepaid data SIM	Some people use a separate prepaid data SIM. Check that the camera supports that carrier first.

HEADS UP

Prices change

Camera data plans are repriced often and vary by carrier and region. The figures above are examples from the maker's own 2026 price list. Confirm the price on the maker's or carrier's website before you sign up, and read what happens if you run out of data mid-month.

Keeping the bill down

- Use motion zones so the camera ignores the road, trees and the pasture (Chapter 25).
- Shorten clip length in the camera's settings.
- Record to a microSD card in the camera where supported, and only send alerts over cellular.
- Check the app's data usage screen after the first week and adjust.

SCAM ALERT

"Unlimited" SIM offers from strangers

Be wary of online sellers offering cheap "unlimited lifetime" SIM cards for cameras. They may be resold lines that get shut off without warning. Buy plans from the camera maker or a carrier you can call.

CHAPTER 14

Trail-Camera Style Options

Hunters have used **trail cameras** for years: rugged, battery-powered boxes strapped to a tree that snap a photo when something moves. **Cellular trail cameras** send those photos to a phone app. Brands such as Tactacam, Spypoint, Moultrie and GardePro make them.

WHAT THIS DOES FOR YOU

What it does for you

A trail camera can watch a far gate, a back field, a hunting stand or a cabin for months on a set of batteries, and it's easy to move. It's a low-cost way to see what's going on far from the house.

How they differ from security cameras

	Cellular trail camera	Cellular security camera
Main output	Photos (some send short video)	Video clips and live view
Live view	Usually limited or none	Usually yes
Talk-back, siren	No	Often yes
Battery life	Long; often AA batteries	Rechargeable; solar helps
Plans	Often priced by number of photos	Priced by data

Things to check

- **Which carrier** it uses at your spot. Trail camera makers often sell versions tied to one carrier.
- **Plan cost**: monthly and yearly options, and whether extra cameras cost less. Check the maker's own plan page; prices change.
- **Night photos**: "no-glow" infrared is less visible to people than "low-glow".
- **Theft**: use a lock box and a cable lock. Many apps can show the camera's location, but don't count on getting it back.

HEADS UP

Trespass and privacy still apply

A trail camera on your own land is generally fine, but aim it at your property, not a neighbor's house or a public road where people expect privacy. See Chapter 26.

PART 4

Getting Internet to the Outbuildings

Why Wi-Fi fades out on the way to the barn, and the three ways to bring it there: mesh and outdoor access points, point-to-point wireless bridges, and buried cable.

CHAPTER 15

Why Wi-Fi Fades Out by the Barn

Your router is designed to fill a house, not a farmyard. Its signal weakens with distance, and some materials soak it up almost completely.

What blocks Wi-Fi outdoors

Obstacle	What it does
Distance	Every doubling of distance cuts the signal sharply. A router indoors rarely reaches far past the yard.
Metal	Steel siding, metal roofs, grain bins and even foil-backed insulation block Wi-Fi badly.
Exterior walls	Brick, stone and stucco walls take a big bite out of the signal.
Trees and leaves	Leaves hold water, which absorbs Wi-Fi. A link that works in March may struggle in July.
Hills	Wireless needs a line of sight at long distances. A rise in the ground can block it.

WHAT THIS DOES FOR YOU

Why this matters to you

Knowing what's in the way tells you which fix will work. Short, open distances can use mesh or an outdoor access point. Long or obstructed distances need a bridge with antennas aimed at each other, or a cable.

Line of sight

Line of sight means you could see one antenna from the other with nothing in between. For long-distance wireless, it's the single most important thing. Stand at the house and look toward the barn: if trees or a hill hide it, plan to mount antennas higher, or go around the obstacle.

TIP

Look from the roofline, not the porch

A link that's blocked at head height may be clear from the eaves of the house to the peak of the barn. Higher mounting is often the cheapest fix.

CHAPTER 16

Mesh Wi-Fi & Outdoor Access Points

When the outbuilding isn't too far away, the simplest fix is to add another Wi-Fi point that repeats your network closer to it.

Mesh Wi-Fi

A **mesh** system uses two or more matching units that work as one network. You place one near the router and others toward the far end of the house. The Mesh Wi-Fi guide in this series covers setup in detail. For rural use, the trick is to put a unit on the side of the house *facing* the barn, close to a window.

Outdoor-rated access points and mesh units

Several makers sell weatherproof mesh units or **outdoor access points** that mount on an outside wall or a pole. They're designed for rain, snow and summer heat, and can push Wi-Fi out across a yard.

1. Pick an outdoor unit that matches your mesh brand, or an access point from the same family as your router.
2. Mount it on the outside of the house facing the barn, under an eave if possible.
3. Power it from a weatherproof outlet or through its network cable (many use **PoE**, Power over Ethernet, so one cable carries both power and data).
4. Run the app's setup and check the signal from the barn door.

WHAT THIS DOES FOR YOU

What it does for you

Wi-Fi in the yard, the garden and the near outbuildings, so Wi-Fi cameras, a phone and a smart plug all work out there without separate data plans.

HEADS UP

Wireless repeating halves the speed

A mesh unit that connects to the next one wirelessly uses some of its capacity just relaying. Each hop is slower. For anything more than one hop, consider a cable or a dedicated bridge.

STAY SAFE

Outdoor power

Any outlet used outdoors should be GFCI-protected (the kind with Test and Reset buttons) and have a weatherproof cover rated for use while plugged in. If there isn't one where you need it, have an electrician add it.

CHAPTER 17

Point-to-Point Wireless Bridges

A **point-to-point bridge** is a pair of small radios with directional antennas. One mounts at the house, the other at the barn, and they aim at each other. Together they act like an invisible network cable, carrying your home internet across the yard or field.

WHAT THIS DOES FOR YOU

What it does for you

Full-speed internet at the barn, shop or a second house, with no trench to dig and no monthly fee. Once it's there, you can plug in an ordinary router or access point and put as many Wi-Fi cameras out there as you like.

Examples and their rated ranges

Example	Type	Maker's rated range
Ubiquiti UniFi Building-to-Building Bridge	Pre-paired 60 GHz kit with 5 GHz backup	Up to 500 m (about 1,640 ft)
Ubiquiti airMAX NanoStation 5AC Loco	5 GHz radio; two make a link	10+ km
TP-Link Pharos CPE210	2.4 GHz outdoor radio; two make a link	5 km+

These are the makers' best-case figures with clear line of sight. Real-world range is often less, especially through trees. A farm link of a few hundred feet to a few thousand feet is well within what these kinds of products are built for.

GOOD TO KNOW

Pre-paired kits are the easy way

Some kits, like Ubiquiti's Building-to-Building Bridge, come with the two radios already paired. Others have to be set up as an access point and a station in their settings, which takes more know-how.

Setting one up, in outline

1. Plug one radio into your router at the house, using the power adapter in the box (most are PoE).
2. Mount it high on the house, aimed at the barn, with a clear view.
3. Mount the second radio on the barn, aimed back at the house.
4. Plug the barn radio into an access point, a small switch or a camera there.
5. Fine-tune the aim using the signal lights or the app, a little at a time.

STAY SAFE

Mounting high means ladders

Radios work best up high, which means ladder work on a roof edge or barn peak. Read Chapter 21 first, never work near power lines, and don't hesitate to get help for anything above a first-floor eave.

HEADS UP

Lightning and grounding

Equipment on poles and rooftops is exposed to lightning. Follow the maker's grounding instructions, and consider surge protection on the cable where it enters the house.

CHAPTER 18

Buried Cable vs Going Wireless

Sometimes a cable really is the best answer. A buried line is unaffected by trees, weather or aiming, and it can carry power to the camera too.

Your choices

Option	What to know
Outdoor-rated network cable	Good up to about 100 meters (328 feet) per run. Use cable rated for direct burial or run it in conduit. Can carry PoE power to cameras.
Fiber-optic cable	Goes much farther and is immune to lightning surges between buildings. Needs small converter boxes at each end.
Wireless bridge	No digging, no cable to damage. Needs line of sight (Chapter 17).

WHAT THIS DOES FOR YOU

What it does for you

A cable laid once can serve the barn reliably for many years with nothing to adjust. It's often the best choice when you're already trenching for electric or water.

Before anyone digs

1. Call **811** a few days ahead so utilities mark their buried lines.
2. Find your own private lines too: the barn's electric feed, propane, water and septic.
3. Check with an electrician about burying network cable near electric lines and about lightning protection between buildings.
4. Use conduit where tractors or trucks will drive over the trench.

STAY SAFE

Electricity between buildings

Network cable between two buildings with separate electrical service can carry dangerous surges in a lightning storm. This is one reason many installers use fiber or a wireless bridge between buildings. Ask a licensed electrician if you're unsure.

PART 5

Power: Solar, Batteries & Outages

Keeping cameras and sensors running far from an outlet and through a storm, and installing them without getting hurt.

CHAPTER 19

Battery & Solar Cameras

Most cameras that go far from the house run on a rechargeable battery. A small **solar panel** trickles power back in during the day, so you rarely have to take the camera down to charge it.

WHAT THIS DOES FOR YOU

What it does for you

No wiring and no outlet needed. A solar camera on a fence post at the gate can run for months without a visit.

How much sun is enough?

It depends on the camera and how much it records. Reolink, for example, says some of its solar models can keep running on about an hour of direct sun a day for normal motion recording, while continuous recording needs more. Its quick-start guide adds that weather, season and location all affect output.

Placing the panel

1. Face the panel **south** (or west) here in the Northern Hemisphere.
2. Tilt it toward the sun rather than laying it flat.
3. Keep it out of shade from trees, eaves and the barn. Even a small shadow cuts output a lot.
4. Check the app's battery level over the first couple of weeks, and again in December when days are short.
5. Brush off snow after a storm if you can reach it safely from the ground.

HEADS UP

Ohio winters

Short days, cloudy weeks and snow cover mean a panel that keeps up easily in June may fall behind in January. Turning down sensitivity or clip length in winter helps the battery last.

CHAPTER 20

When the Power Goes Out

When rural power fails, it can be off for hours. Here's what keeps working, what doesn't, and how to bridge the gap.

What keeps working on its own

- **Battery driveway alarms**: the sensor keeps working; the receiver needs batteries or a backup if it plugs into the wall.
- **Battery and solar cameras** keep recording.
- **Cellular cameras** keep sending alerts as long as the cell tower has power.

What stops

- Your router, modem, Starlink dish or fixed-wireless receiver, and with them every Wi-Fi camera and sensor hub.
- Plug-in cameras and recorders (NVRs).
- Long-range sensor hubs, so phone alerts stop even though the sensors are fine.

A battery backup (UPS) for your internet

A **UPS** (uninterruptible power supply) is a battery box that sits between the wall and your equipment and takes over instantly when the power fails. Plugging your modem, router and sensor hub into one keeps alerts flowing for a while during an outage.

1. Add up what you'll plug in. Starlink, for example, says its Standard kit draws about 75 to 100 watts on average, so it needs a larger UPS than a modem and router alone.
2. Choose a UPS rated well above that total and check its runtime chart.
3. Plug the internet gear and hub into the battery-backed outlets, not the surge-only ones.
4. Test it: unplug the UPS from the wall and see how long things stay up.

STAY SAFE

Generator safety

If you run a portable generator, the U.S. Consumer Product Safety Commission says to run it outdoors only, at least 20 feet from the house, with the exhaust pointed away, and never in a garage, basement or shed. Opening windows is not enough ventilation. Have battery-backed CO alarms on every level of the home.

CHAPTER 21

Ladders, Wiring & Weather: Safe Installation

Most rural security gear goes up high: on barn peaks, eaves and poles. A fall from a ladder is the biggest real danger in this whole guide. Please read this chapter even if you plan to hire the ladder work out.

Ladder basics

- **Set the angle right**: the foot of an extension ladder should be about one foot out for every four feet of height to where it rests (OSHA's 1-to-4 rule).
- **Keep three points of contact** when climbing: two hands and a foot, or two feet and a hand.
- **Extend the ladder at least 3 feet above** a roof edge or landing you'll step onto.
- **Carry tools in a pouch or raise them with a rope**, not in your hands.
- **Have someone with you** to steady the ladder and call for help if needed.

STAY SAFE

Power lines

OSHA says to keep ladders and tools at least **10 feet** from overhead power lines; the CPSC advises never placing a ladder near one at all. Metal ladders conduct electricity. Look up before you raise a ladder, and carry long ladders horizontally. If a ladder starts to fall into a line, let it go and call the power company.

Wiring

- Plug outdoor gear only into GFCI-protected outlets with in-use weatherproof covers.
- Use outdoor-rated extension cords only as a temporary measure, never stapled or buried.
- Hard-wiring a camera or floodlight to house or barn circuits is a job for a licensed electrician if you're not experienced.
- Seal any hole you drill through a wall with outdoor caulk so water and insects stay out.

Weather and timing

- Don't climb in wind, rain or ice, or on wet barn roofs.
- Pick a dry, mild day and work in daylight.
- Watch for wasps' nests under eaves and in barn rafters before you climb.

FROM BILL

When to get help

There's no shame in having someone else do the high work. Ground-level jobs like setting up apps, testing signals and placing sensors are easy to do yourself. For anything on a roof, a pole or a barn peak, I'm glad to help, or I'll tell you honestly if it's a job for an electrician or a roofer.

PART 6

Living with Limited Internet

Starlink, fixed wireless and other rural options, how to keep cameras from swamping a slow or capped connection, and why recording locally is your friend.

CHAPTER 22

Starlink, Fixed Wireless & Other Rural Internet

Good security cameras need decent internet, especially upload speed. Out in the country you may have more choices than you think.

The common rural options

Type	How it works
Satellite (Starlink)	A dish on the roof or a pole talks to low-orbit satellites. Needs a clear view of the sky. Widely available.
Fixed wireless	A small antenna on your house aims at a local provider's tower. Speed depends on the provider and line of sight to the tower.
Cellular home internet	A box that uses the cell network, offered by the big wireless carriers in some areas.
DSL, cable or fiber	Where the lines reach. Fiber is often the best for cameras if it's available.

Find out what's available at your address

1. Go to the FCC's **National Broadband Map** at broadbandmap.fcc.gov.
2. Type your address. The map shows which providers report service there and what technology and speeds.
3. Use the filter to show slower services too; services under 25 Mbps are hidden on the default view.
4. If the map is wrong, you can file a challenge right from your location's page.

Starlink plans, in brief

As of November 2026, Starlink's U.S. residential page lists plans starting at **$55 a month** (100 Mbps tier), **$85** (200 Mbps tier) and **$130** (Residential Max). Prices and availability vary by address, and the equipment is extra. Starlink also offers a low-cost **Standby Mode** for existing customers that pauses full service while keeping a very slow connection for basic messages.

TIP

Check the sky before you order

The Starlink app has a free tool that scans the sky for trees and buildings that would block the dish, and you don't need an account to use it. See "Ways Your Rural Security Can Make Life Easier".

HEADS UP

Ask about upload speed and data limits

When comparing any provider, ask: what's the **upload** speed, and is there a monthly data cap or a slowdown after a certain amount? Several cameras uploading video add up.

CHAPTER 23

Cameras on a Slow or Capped Connection

You don't need fiber to run cameras. You just need to be thoughtful about how much video leaves the house.

WHAT THIS DOES FOR YOU

What it does for you

Your cameras keep working, your TV streaming doesn't stutter every time a deer walks by, and you don't get a surprise when you hit a data limit.

Ways to cut camera upload

1. **Record events, not all day.** Set cameras to record only when they detect motion, unless you have a reason to record continuously.
2. **Use motion zones** so cameras ignore trees, roads and pastures (Chapter 25).
3. **Shorten clips.** A 15- or 20-second clip is usually enough to see what happened.
4. **Lower the cloud upload quality** if the app offers it, while keeping full quality on the local card.
5. **Record locally** to a microSD card or a recorder in the house (Chapter 24), and only send alerts and thumbnails out.
6. **Go easy on live view**, which streams continuously while you watch.

Check what your cameras are really using

Many routers and mesh apps show which devices use the most data. Look for your cameras after a week. If one stands out, it's usually set to record continuously or has a busy motion zone.

HEADS UP

Cloud backups and big uploads

Phones backing up photos, computers backing up files and cameras uploading video all compete for the same upload. If things feel slow in the evening, check whether a backup is running.

CHAPTER 24

Recording Locally vs the Cloud

Every camera has to save its video somewhere. The choice matters more in the country, where internet is precious and may go down.

	Local (microSD card or recorder)	Cloud (maker's servers)
Monthly cost	None	Usually a subscription
Works if internet is down	Yes, keeps recording	No, until it reconnects
Uses your upload	Little or none	Every clip
If the camera is stolen	The card may go with it	Clips already saved are safe
Viewing	Varies; some need the card removed	Easy, from the app anywhere

An example: Arlo Go 2 and its microSD card

Arlo says the Go 2 can save recordings to a microSD card (sold separately), turned on in the app's storage settings with **Record Locally**. To view those recordings you remove the card and read it on a computer. That makes local storage a good backup for when the connection drops, rather than a replacement for checking clips on your phone.

Recorders in the house (NVRs)

A **network video recorder** (NVR) is a box that records from several cameras onto a hard drive in your house. It's common with wired camera systems and is covered in the Reolink & Wired Camera Systems guide. For a farm with a wireless bridge to the barn, an NVR lets you record all the barn cameras without any cloud plan.

WHAT THIS DOES FOR YOU

What it does for you

Video is saved even when your internet is down, and there's no monthly fee per camera. Many systems let you check in from your phone too.

TIP

Hide the recorder

Put the recorder or the hub somewhere out of sight, not next to the front door, so it doesn't walk out with an intruder. Plug it into the UPS from Chapter 20.

PART 7

Animals, Neighbors, the Law & Scams

Keeping wildlife and livestock from flooding you with alerts, being a good neighbor with your cameras, and the scams aimed at rural homeowners.

CHAPTER 25

Taming False Alarms: Deer, Livestock & Weather

A system that alerts you 40 times a night for raccoons trains you to ignore it. Getting false alarms down is the single biggest improvement you can make.

For cameras

1. **Draw motion zones** in the app around only the driveway, the door or the gate, leaving out pastures, trees and the road.
2. **Turn on person or vehicle detection** if your camera offers it (some brands include it free, others need a plan), and turn off alerts for "all motion" or animals.
3. **Lower sensitivity** a step at a time until branches and shadows stop triggering it.
4. **Set a schedule** so the barn camera alerts at night but stays quiet during chores.

For driveway alarms

- Raise a motion sensor to bumper height and aim it across the drive, so it sees vehicles more than small animals.
- Keep grass and branches trimmed in front of it.
- If deer still set it off, a magnetic probe (Chapter 7) ignores animals entirely.

Livestock and pets

- Don't point motion sensors into a paddock or across a pasture where animals graze.
- Inside a barn with animals, use door sensors rather than motion sensors.
- Remember that a camera's infrared light at night attracts insects and spiders, which trigger motion. Clean the lens and housing regularly.

WHAT THIS DOES FOR YOU

What it does for you

When the chime goes off or your phone buzzes, you'll know it's worth a look.

HEADS UP

Wind, snow and sun

Blowing snow, heavy rain, swaying branches and sunlight moving across the ground can all trigger motion. Recheck your zones when the seasons change.

CHAPTER 26

Privacy, Trespass & Being a Good Neighbor

Cameras on your own land are generally fine, but they come with responsibilities. This chapter is general information, not legal advice. Laws vary, so if you have a specific concern, ask a lawyer or your local sheriff's office.

Good-neighbor habits

- **Aim at your own property.** Avoid pointing cameras into a neighbor's windows, yard or barn.
- **Use privacy zones** (blacked-out areas many apps offer) to block a neighbor's house or a public road.
- **Be careful with sound.** Laws about recording conversations vary from state to state; many people simply turn off audio recording on outdoor cameras.
- **Talk to neighbors** if a camera faces a shared lane or property line. A friendly word avoids misunderstandings.

Trespassing

If you find someone on your property who shouldn't be there, don't confront them. Stay inside or keep your distance, note what you can (vehicle, direction, time), and call 911 if you feel threatened or the sheriff's non-emergency line otherwise. Your camera footage can help, so save the clip right away.

STAY SAFE

Never confront

No piece of equipment is worth your safety. Let law enforcement handle trespassers.

Signs

"Video surveillance" and "No trespassing" signs are inexpensive and can discourage people from coming up the lane in the first place. Rules about how land must be posted vary, so check with your county if you're relying on signs for legal purposes.

Sharing footage

- Share clips with law enforcement when asked about a crime.
- Think twice before posting footage of identifiable people on social media.
- Keep the clips that matter: download or save them, because many systems delete older video automatically.

CHAPTER 27

Scams Aimed at Rural Homeowners

Security and internet are both areas where scammers follow the customers. Here are the ones worth knowing about.

SCAM ALERT

The door-to-door security salesman

Someone shows up saying your current alarm company has gone out of business, or that there's been a break-in nearby and they can install a system today. The FTC warns that high-pressure tactics are a red flag. Never sign on the spot. Take their card, research the company, and get other quotes.

Your three-day right to cancel

Under the FTC's **Cooling-Off Rule**, if you sign a contract for a home security system in your own home, you generally have **three business days to cancel**, without giving a reason, even if the equipment has already been installed. The seller must tell you about this right and give you a cancellation form.

Other scams to watch for

- **Fake internet deals**: ads or calls offering satellite or Starlink service at a price far below the real one, asking for payment by gift card, wire or app. Order only through the provider's own website or a store you know.
- **Too-good-to-be-true cameras**: social media ads for "military-grade" solar cameras at a fraction of the usual price, from sites you've never heard of. They often never arrive.
- **Fake tech support**: a pop-up or call saying your camera account is hacked and asking you to install remote-access software or pay. Close it and call the company using the number on its official website.
- **Phishing emails** that look like they're from your camera company asking you to "verify" your password. Open the app directly instead of clicking the link.

TIP

Protect your camera accounts

Use a strong, unique password for each camera app and turn on two-step verification. That's the best protection against someone else watching your cameras.

SCAM ALERT

Never pay with gift cards

No real security company, internet provider or tech support service asks for payment in gift cards. If anyone does, it's a scam. Hang up.

PART 8

When to Call Bill & Your Cheat-Sheet

An honest word about when a hand is worth it, and a one-page summary of the whole guide.

CHAPTER 28

When to Call Bill

I've written this guide so you can do a lot of this on your own. But part of being helpful is being honest about when a hand saves you time, money or a fall from a ladder. Here's my plain advice.

Times it's worth a call

- **Planning the whole property**: walking it with you, checking signal at each building and suggesting the simplest mix that does the job.
- **Getting internet to the barn or shop**: aiming and setting up a wireless bridge, or an outdoor access point.
- **Choosing a cellular camera and plan** that actually works with the strongest carrier at your gate.
- **Setting up camera apps**, motion zones and alerts on your phone and on a family member's phone.
- **Backup power** for your internet equipment and sensor hub.
- **A flood of false alarms** you can't seem to tame.
- **Anything that feels like a scam**, or a contract someone wants you to sign today.

This guide pairs with my **Security Cameras** service, where I help you choose, install and set up cameras on the house and around the property.

What working with me is like

I work at your pace, in your home here in Portage County or remotely over the phone and internet. I explain what I'm doing in plain words, I don't sell you gadgets you don't need, and I'll tell you honestly when a job needs an electrician or a roofer instead. I bring more than 30 years of professional experience to every visit.

FROM BILL

How to reach me

Call or text **(330) 200-8042** or book a time at **billshometech.com/book**. My help is **$49 remote · $99 in your home**. Bill's Home Tech serves Portage County, Ohio. No question is too small.

GOOD TO KNOW

You may meet Sophie

When you call or visit billshometech.com, you may be greeted by **Sophie**, my AI receptionist. She can answer simple questions and get you on my schedule. The actual help always comes from me.

Thank you for letting me help you look after your place. Take your time, stay safe on the ladder, and remember I'm only a phone call away.

— Bill

CHAPTER 29

Your Rural Security Cheat-Sheet

The whole guide, boiled down. Keep a copy by the kitchen phone.

Which tool for which job

I want to…	Use this
Know when a car turns in	Driveway alarm: motion sensor (easy) or magnetic probe (no animals). Chapters 5–7.
Know when the barn opens	Door sensor, ideally long-range (LoRa). Chapters 8–9.
See the gate with no Wi-Fi	Cellular camera or cellular trail camera. Chapters 12–14.
Internet at the barn	Mesh or outdoor access point if close; wireless bridge or cable if far. Chapters 16–18.
Keep going in an outage	Battery/solar cameras, cellular cameras, and a UPS for the router. Chapters 19–20.
Too many alerts	Motion zones, person/vehicle detection, lower sensitivity, schedules. Chapter 25.

Safety, in order

1. Ladders: 1-to-4 angle, three points of contact, someone holding it.
2. Stay at least 10 feet from overhead power lines.
3. Call 811 before you dig.
4. GFCI outlets with in-use covers outdoors; an electrician for hard-wiring.
5. Generators outdoors only, at least 20 feet from the house.
6. Never confront a trespasser. Call the sheriff or 911.

Write it down once

Keep handy	
Driveway alarm battery type / last changed	_____
Camera app and sign-in email	_____
Cellular camera carrier and plan renewal date	_____
Internet provider and support number	_____
Where the UPS is and what's plugged in	_____
Sheriff's non-emergency number	_____

When something's wrong, in order

1. No alerts: check the internet and power at the house, then the hub or receiver.
2. Camera offline: check its battery, then its Wi-Fi or cellular signal.
3. Too many alerts: tighten motion zones and lower sensitivity.
4. Driveway alarm silent: fresh batteries in the sensor, then test by walking past.
5. Someone wants money today: stop, don't pay, and check with someone you trust.
6. Still stuck: call Bill at (330) 200-8042.

FROM BILL

I'm here when you need me

Call **(330) 200-8042** or visit **billshometech.com/book**. $49 remote · $99 in your home.